
TRANSLATION TO ENDF/B AND "PHYSICS"
CHECKING OF CROSS SECTIONS FOR SHIELDING

Final Report

Contract No. DASA01-69-C-0029 Defense Atomic Support Agency Washington, D.C. 20305

ENDF-130

Submitted by: Donald J. Dudziak



Research Laboratories for the Engineering Sciences

University of Virginia

Charlottesville '

This document has been approved for public release and sale; its distribution is unlimited.

ENDF-130 Report No. NE-3383-104-69U

November 1969

TRANSLATION TO ENDF/B AND "PHYSICS" CHECKING OF CROSS SECTIONS FOR SHIELDING

Final Report

Contract No. DASA01-69-C-0029 Defense Atomic Support Agency Washington, D.C. 20305

ENDF-130

Submitted by:
Donald J. Dudziak

This work was sponsored by the Defense Atomic Support Agency under NWER Subtask PC100.

This document has been approved for public release and sale; its distribution is unlimited.

Division of Nuclear Engineering
RESEARCH LABORATORIES FOR THE ENGINEERING SCIENCES
SCHOOL OF ENGINEERING AND APPLIED SCIENCE
UNIVERSITY OF VIRGINIA
CHARLOTTESVILLE, VIRGINIA

Report No. NE-3383-104-69U ENDF-130 November 1969

Copy No. ___

ABSTRACT

Evaluations of neutron interaction and photon production cross sections for sodium, magnesium, chlorine, potassium, and calcium have been translated from a modified-UK format into ENDF/B format. The data have been reviewed and revised to a minor extent, and can be used by the LAPH code to generate multigroup photon production cross section matrices. All data sets have been transmitted to the University of California, Los Alamos Scientific Laboratory, to the National Neutron Cross Section Center at BNL, and to the Radiation Shielding Information Center at ORNL. Several "physics" checks have been proposed for the photon data, and a FORTRAN IV code, PHOX, has been written to incorporate some of these checks.

TABLE OF CONTENTS

		F	PAGE
ABS ⁻	TRACT .		; i i
LIS	T OF II	LLUSTRATIONS	ψi
1.	Intro	duction And Summary	1
2.	Trans	lations of Na, Mg, Cl, K, and Ca To ENDF/B Format	2
		Procedures	2
		2.1.1. Additions to Files I and 3	3
		2.1.2. Transition Probability Arrays	3
		2.1.3. Residual Photon Production (MT = 110)	4
	2.2.	Major Modifications of the Data	4
		2.2.1. Photon Production from Inelastic Scattering	4
		2.2.2. Photon Production by the (n,p) and (n,α)	
		Reactions in Potassium	5
		2.2.3. Photon Production by the (n,p) Reaction in Calcium	5
	2.3.	Alterations to the Data During Translation to	
	,,	ENDF/B Format	6
		2.3.1. Normatizations	6
		2.3.2. Miscellaneous	7
	2.4.	Unresolved Inconsistencies	10
	_•	2.4.1. Sodium	10
		2.4.2. Magnesium	H
		2.4.3. Chlorine	
		2.4.4. Potassium	11
		2.4.5. Calcium	12
	2.5.	Distribution of the Data	12
	2.6.	Translation Codes: LUTE and LATEX	12
3.	Propo	sed "Physics" And Internal Consistency Checks	14
	3.1.	Introduction	14
	3.2.	File 3 Checks	14

TABLE OF CONTENTS (continued)

		· · · · · · · · · · · · · · · · · · ·	PAGE
	3.3.	File 14 Checks	15
	3.4.	File 15 Checks	17
	3.5.	File 23 Checks	18
	3.6.	File 24 Checks	20
	3.7.	File 27 Checks	20
4.	PHOX,	A "Physics" Checking Code for Photon Data in the	
	ENDF/I	B Data File	21
	4.1.	Introduction and Summary	21
	4.2.	PHOX Code and Subroutines	22
		4.2.1. CKHD(FILE)	22
		4.2.2. FIL3(AWR)	22
		4.2.3. FILI4(N)	23
		4.2.4. FILI5(N)	23
		4.2,5. ESEGPR(N)	23
		4.2.6. STATE(LG)	24
	4.3.	Input and Output Specifications	24
		4.3.1. PHOX Input	24
		4.3.2. PHOX Output	24
	4.4.	Burroughs B5500 Computer Fortran IV Complier Features	24
APP	ENDIX	A: Corrections and Alterations to the Data in UK Format	26
	Α.Ι.	UK Material Number (NIN) 205 * <u>SODIUM</u>	28
		A.I.I. Data File Changes	28
		A.1.2. Normalization Value from CHECKER	32
	A.2.	UK Material Number (NIN) 206 * MAGNESIUM	36
		A.2.1. Data File Changes	36
	A.3.	UK Material Number (NIN) 221 * CHLORINE	38
		A.3.1. Data File Changes	38
	A.4.	UK Material Number (NIN) 227 * POTASSIUM	40
		A.4.I. Data File Changes	40

TABLE OF CONTENTS (continued)

					P	AGE
A.5.	UK Material Number (NIN) 23	* CALCIUM				42
	A.5.1. Data File Changes.		•	•	•	42
APPENDIX I	3: Alterations to the Data in	Transforming to ENDF/B.	•			45
B.I.	ENDF/B Material Number (MAT	5001 * <u>SODIUM</u>	•			47
	B.I.I. Data File Changes .		•	•		47
B.2.	ENDF/B Material Number (MAT	5002 * MAGNESIUM	•	•		51
	B.2.1. Data File Changes .			•		51
В.3.	ENDF/B Material Number (MAT	5004 * CHLORINE				56
	B.3.1. Data File Changes .	·	•	•	•	56
B.4.	ENDF/B Material Number (MAT	5005 * POTASSIUM				57
	B.4.1. Data File Changes .	· · · · · · · · · · · · · · · · · · ·	•			57
B.5.	ENDF/B Material Number (MAT	5006 * <u>CALCIUM</u>	•		•	58
	B.5.1. Data File Changes .		•	•	•	58
APPENDIX (C: INDEX'ed Listing of PHOX		•		•	61
ACKNOWLED	GEMENT		•		•	99
REFERENCES	S					101

LIST OF ILLUSTRATIONS

					PAG	Œ
FIGURE 1.	Elastic Secondary No	leutron Angular	Distributions.			8
FIGURE 2.	Elastic Secondary No	leutron Angular	Distributions.		•	9

I. Introduction And Summary

As part of the ENDF/B⁽¹⁾ effort, a format⁽²⁾ was devised for storing photon production and photon interaction data. In order to de-bug the photon production format, sodium data from a recent evaluation by Drake $\underline{e} + \underline{a} \underline{I}^{(3)}$ were translated from a modified UK Data File format into the ENDF/B Data File format (cf. Ref. 2 for a listing of this translation). The translation was performed by a special-purpose FORTRAN IV code called LUTE. Because the entire sodium evaluation was of interest to the Shielding Subcommittee of the Cross Section Evaluation Working Group (CSEWG), the University of California, Los Alamos Scientific Laboratory undertook the translation of the neutron interaction data also. This latter translation was performed with the LATEX code, an extended version of the LATE code which had been previously used for translations of 6 Li and 7 Li. $^{(5)}$ Later, the Los Alamos Scientific Laboratory undertook the translation by Drake $\underline{e} + \underline{a} \underline{I}$, $^{(3)}$ as well as a preliminary analysis of the translation procedures for chlorine, potassium and calcium.

This report describes in §2 the procedures and data revisions for the translations of Na, Mg, Cl, K, and Ca. Details of the revisions are given in Appendices A and B. Proposals for "physics" and internal consistency checks which might, in part, be incorporated in a checking code are given in §3. Particular emphasis is placed on checks which are applicable to the photon data. A code called PHOX was written to perform checks on the photon data. It is described in detail in §4, and a listing is given in Appendix C. The translation codes, LUTE and LATEX, are described in a separate report. For purposes of the present report the modified and extended UK Data File format used by Drake et al. will be referred to as simply the "UK format", and the entirety of their data as the "UK Data File".

2. Translations Of Na, Mg, CI, K, and Ca To ENDF/B Format

The materials which were translated are identified on each UK-format card image by a nuclide identification number (NIN), and on each ENDF/B-format card image by a material number (MAT). Listed below in Table I are the materials and their corresponding NIN and MAT numbers.

TABLE I.

Material Identifying Numbers

<u>Material</u>	NIN(UK)	MAT(ENDF/B)
Na	205	5001
Mg	206	5002
CI	221	5004
K	227	5005
Ca · · · · · · · · · · · · · · · · · · ·	231	5006

2.1 Procedures

The translation procedure used was to start with the materials on data tapes in UK format, and attempt a run thru the LUTE and LATEX codes. Several iterations were required for each material before the UK-format tape had been corrected sufficiently to allow a successful translation. After correcting as many errors as the translation codes could detect (generally clerical errors, mispunches, cards out of sequence or missing, etc.), the data in both listed and plotted form were scanned visually for any obvious inconsistencies or other errors. Appendix A documents in minute detail the corrections and alterations to the UK Data File which have been made since July 1968. Appendix B documents similar information for the ENDF/B Data File.

Construction of a corresponding ENDF/B Data File for each material required several changes and additions (as opposed to corrections), which are described in detail in reference 6. In summary, these primarily consisted of the three changes described below.

2.1.1. Additions to Files 1 and 3

A complete File I was created for each material, including a table of contents and an index. A tabular section for the average cosine of the angle of elastic scattering in the laboratory system was automatically created by LATEX for File 3. This latter table of $\overline{\mu}_{LAB}$ values was calculated using the angular distributions of secondary neutrons from elastic scattering, as given in File 4 (MF = 4, MT = 2). The values of $\overline{\mu}_{LAB}$ were extended down to the lowest energy for which an elastic scattering cross section is given in File 3 (MF = 3, MT = 2), using a value $\overline{\mu}_{LAB} = \frac{2}{3(AWR)}$ at this lowest energy. This value was also used at 0.75 E₃, where E₃ is the lowest incident neutron energy for which an angular distribution is given in File 4.

2.1.2. Transition Probability Arrays

Because of an inherent difference between the allowable UK and ENDF/B formats for photon production cross sections, the photon production from inelastic scattering to discrete levels was not translated completely by the code LUTE. The ENDF/B format $^{(2)}$ allows not only photon production cross sections (slightly disguised) or yields, as in the UK format, but also allows the alternate use of transition probability arrays when the level energies are well established. Thus, these arrays were entered for all levels up to the highest level for which the level energy and decay scheme are well established. However, photon production data were often given in the UK Data File for incident neutron energies above the energy of this highest level (denoted $\mathbf{E_d}$), so other provisions had to be made for storing these data in ENDF/B format. The method chosen was to use photon production cross sections for incident neutron energies above $\mathbf{E_d}$, exactly as they are given in the UK format. In order to accomplish this conveniently, a new reaction type number was defined for ENDF/B, as discussed in the next section.

2.1.3. Residual Photon Production (MT = 110)

A new reaction type number, MT = 110, was defined and used for residual photon production by incident neutrons with energies greater than E_d . Any inelastic scattering reaction (MT = 5 thru 14 and 51 thru 80) section with incident neutron energies greater than E_d automatically has the photon production cross sections above this energy translated by LUTE to a subsection of photon production cross sections within MT = 110. Also, the first time this case is encountered by LUTE, an MT = 110 section for File 3, with unit cross section, is generated. Thus, the photon production cross sections appear in File 15 under the guise of yields, but processing codes such as LAPH will properly construct photon production cross sections from the combined data of Files 3 and 15.

2.2. Major Modifications of the Data

Only the three major changes requiring discussion are given in this section. These changes were made in converting to ENDF/B format, that the UK Data File was not altered. Detailed minor corrections or alterations to the UK Data File are given in Appendix A. Minor changes to the ENDF/B Data File are given in Appendix B, and minor alterations for consistency and format purposes are discussed in §2.3.

2.2.1. Photon Production from Inelastic Scattering by $^{37}{\rm CI}$

Level excitation cross sections for reaction types 5 through 14 and 51 through 53 are for the 1.22 MeV through 6.10 MeV levels, respectively, of 35 Cl. However, photon production cross sections in the UK Data File are given for the corresponding levels only for reaction types up to 51. Reaction types 52 through 54 are used to present photon production cross sections for three levels of 37 Cl (viz., 1.728, 3.087 and 3.71 MeV). Since the transition probability arrays in the ENDF/B Data File for chlorine do not contain the 37 Cl levels, the photon production cross sections for these levels were included in their entirety in the residual photon production section (MT = 110). That is, the parameter E_d was zero for MT = 52, 53 and 54. Photon production

for incident neutron energies below 5.22 MeV ($\rm E_d$ for $^{35}\rm CI$) would thus be given only for $^{35}\rm CI$ by the transition probability arrays and corresponding excitation cross sections. Excitation cross sections for the levels of $^{37}\rm CI$ are not explicitly given in the UK Data File, but are included in the section for total inelastic scattering, reaction type number (RTN) 1004. They presumably are not included in the section for inelastic scattering to the continuum, RTN = 1015.

2.2.2. Photon Production by the (n,p) and (n,α) Reactions in Potassium

Photon production data for the (n,p) reaction in potassium are identified in the UK Data File by reaction type numbers 13121 and 13122. These RTN's are for the (n,p₁) and (n,p₂) reactions in 39 K; i.e., leaving the residual 39 Ar nucleus in the first or second excited states, respectively. Because neutron interaction cross section were given only for the total (n,p) reaction, data for RTN = 13121 and 13122 were combined into one section with MT = 103. This is the ENDF/B reaction type number for the total (n,p) reaction. Angular distributions for these photons were likewise assigned to MT = 103 in File 14.

A similar case occurred for the (n, α_1) reaction in 39 K; i.e., to the first excited state of 36 Cl. Photon production data for this reaction were given in the UK Data File by RTN = |3|4|, and the angular distribution by RTN = |1|4|. The data were placed in the ENDF/B Data File under MT = 107.

2.2.3. Photon Production by the (n,p) Reaction in Calcium

Photon production data for the (n,p) reaction in calcium are identified in the UK Data File by reaction type numbers 13060, 13061, and 13062. These RTN's are for the (n,p₁), (n,p₂), and (n,p₃) reactions in 40 Ca; i.e., leaving the residual 40 K nucleus in one of its first three excited states. Also, photon production data for inelastic scattering to the continuum are given in RTN = 13015 for incident neutron energies from 6.0 to 20.0 MeV, whereas the corresponding excitation cross sections (RTN = 1015) are given for incident neutron energies from 9.0 to 20.0 MeV. Thus, after

consulting with Drake, $^{(8)}$ the photon production from 6.0 to 9.0 MeV was assigned to the (n,p) reaction in ENDF/B (MT = 103). Also, as with potassium, the neutron interaction cross sections were given in the UK Data File only for the total (n,p) reaction, so the data in RTN = 13060, 13061, and 13062 were included in the ENDF/B reaction type number for the (n,p) reaction, MT = 103. In a similar manner, angular distributions of photons from the (n,p_1) , (n,p_2) , and (n,p_3) reactions were assigned to MT = 103.

2.3. Alterations to the Data During Translation to ENDF/B Format

All alterations which were made to the data in UK format were also carried through during translation to ENDF/B format. Since the changes in the UK Data File are documented in detail in Appendix A, they will not be repeated here. There is, however, a class of changes which appears only in the ENDF/B Data File, and those are the ones discussed here. Such changes are typically ones of normalization, consistency between level energies (Q values) and photon energies, etc. The details of the changes appear in Appendix B.

In translating neutron and photon angular distributions to ENDF/B format it was assumed that a zero appearing in the second field of a one-card section with a general classification number (GCN) of 2 or 11 implies an isotropic distribution. The isotropy is explicitly stated for most such cases listed in Tables 4 thru 8 of Reference 3. It was assumed and verified (8) that the UK-format is consistent in this regard.

2.3.1. Normalizations

Data in the UK Data File were never altered to force normalization of neutron and photon angular distributions, or of neutron secondary energy distributions and photon energy distributions. However, all of these data are required in the ENDF/B Data File to be normalized to probability density functions. Thus, all of these normalizations were automatically performed in the translation procedure. Appendix A lists an example of the integrals of the photon angular distributions as they were determined for the


UK Data File. These re-normalization constants are given for information only; they were not used to alter the UK Data File. Assuming a linear interpolation between μ (i.e., $\cos^2\theta$) values, the original distributions were usually normalized to unity, within 1%. Re-normalizations constants are not listed for the secondary neutron angular distributions, but they were usually within about 1% of unity. Some, however, differed from unity by up to about 15% (e.g., in RTN = 2002 for chlorine).


Figures I and 2 show typical plots of data for neutron angular distributions, where the value at $\mu=0.45$ for an incident neutron energy of 4.8 E - I MeV apparently was in error. Correcting this error then introduced a slight error in the normalization, which was in turn corrected.

2.3.2. Miscellaneous

Certain alterations listed in Appendix B were tailored for the LAPH code. (7) They involve no substantive changes in the data, but are necessary to satisfy the ENDF/B format requirements or to structure the data in an optional form which is simpler or more convenient. Examples of this type change are:

- (I) Level energies or Q values in Files 3 and 15 (Option 2), principally in sodium and magnesium, were made consistent with photon energies in File 14. This is required to allow processing codes to correlate level transitions with the angular distributions of the corresponding photons. Any changes of Q value in File 3 were for purely esthetic reasons. A standardization on a particular value was not based upon any new physical data or revelation concerning the correct value among conflicting data. In no case was the difference between conflicting data significant for either data file (i.e., for normal nuclear engineering purposes). In many cases the PHQX code found threshold values lower than theoretically allowed by the Q values, but the values were consistent to within three significant figures so no changes were made in the UK Data File.
- (2) In the magnesium data, section (MT) numbers II, I2, and I3 correspond to the 2.565, 2.736 and 2.803 MeV levels of 25 Mg, for which the decay





-DISIGHU)\DIHU)\SIGHU




FIGURE 2

schemes are not known. However, MT = 14 corresponds to the 2.94 MeV level of 26 Mg, and MT = 51 thru 55 correspond to the 4.12 thru 6.44 MeV levels of 24 Mg, all of which have known decay schemes. In order not to preclude the use of transition probability arrays for these latter levels (MT = 14 and 51 thru 55), the levels of 25 Mg with unknown decay schemes were assigned zero transition probabilities. Such unorthodox transition probability arrays will be flagged by the photon "physics" checking code, PHQX, but will be acceptable to LAPH. They allow a simple, accurate and concise representation of all photon production from well-known level decay schemes.

(3) In the calcium transition probability arrays, MT = 6 corresponds to the first level of 40 Ca (3.35 MeV), which decays by electron-positron emission. In order to correctly compute the resulting annihilation photon source, the energy of this level is listed in File 15 as 0.51 MeV. and the transition probability is assigned the value 2.0. These will be flagged by PHQX as suspicious data.

2.4. Unresolved Inconsistencies

During review of the data several inconsistencies were noted between the UK Data File and the documentation of the data in the Appendices of GA-7829. Also, what seem to be clerical errors appear in these appendices. No changes were made on either the UK or ENDF/B Data File where a question concerning the correct data could not be resolved from the source documentation. However, the questionable data are noted below for possible future revision when time permits.

2.4.1. Sodium

Angular distribution data for secondary neutrons from inelastic scattering to the second (2.08 MeV) level differs considerably between the UK Data File and the documentation (GA-7829, Vol. II, p. A-53). This discrepancy occurs at 8.5 and 9.0 MeV incident neutron energies, where the documentation lists angular distributions identical to that at 8.0 MeV. The UK Data File (RTN = 2006), on the other hand, lists substantially

different distributions, peaking strongly and irregularly about μ = 0. Plots of the data indicate they are also irregular at 7.5 and 8.0 MeV.

Similarly, for the first excited state (0.4392 MeV level) the document and the UK Data: File disagree at various incident energies between 6.0 and 9.0 MeV. Also, even where the data agree it appears from the plots that a discrepancy may occur at μ = -1.0. Though the data were not altered it appears as if a simple extrapolation of the smooth curves to μ = -1.0 would be satisfactory.

2.4.2. Magnesium

Plots of the angular distributions of secondary neutrons from elastic scattering showed irregularities which were not obvious errors, or which were apparently errors but did not seem to be rectifiable by a simple linear interpolation between neighboring points. These occurred at incident neutron energies of 0.19 and 0.68 MeV. A similar case existed at 0.21 MeV, but the data were smoothed for 0.1 $\leq \mu \leq$ 0.4. A comparison with the original documentation in GA-7829, Vol. III, will show the alterations performed.

2.4.3. Chlorine

A plot of the angular distribution of secondary neutrons from elastic scattering shows an irregularity at μ = 1.0 for an incident neutron energy of 15 MeV. At this point the probability density drops abruptly, whereas at adjacent incident energies the probability rather smoothly approaches a maximum at μ = 1.0.

2.4.4. Potassium

Angular distributions for secondary neutrons from inelastic scattering to the 10th through 17th levels (MT = 51 through 57) are not given at all in the UK Data File. However, Vol. 1 of GA-7829 states in Table 7, under "Remarks," that these are isotropic. Thus, isotropic angular distributions were <u>not</u> created by LATEX because of <u>no</u> entry being present in the UK Data File. It may be desireable to add these distributions to both

data files in the future. There seems to be no distinction between isotropic distributions which appear in the UK Data File in the form of a single-card section and those which do not appear at all. Secondary neutron angular distributions at 9.5, 10, 10.5, and 11.5 MeV show radical fluctuations at around $\mu=0.3$. It was not obvious whether these are real or due to clerical errors, and the fluctuations occur for 2 to 3 consecutive data points. Thus, the data were not altered.

2.4.5. Calcium

Data for inelastic level excitation cross sections for the first four levels seem to be displaced in energy between the tabulations in the document and in the UK Data File. This displacement generally occurs for energies above about 3.6 MeV

2.5. Distribution of the Data

Copies of the corrected UK Data File were sent to the Radiation Shielding Information Center (RSIC) at Oak Ridge National Laboratory (ORNL), where a general UK ENDF/B translation code is under consideration. These data were also sent to the Los Alamos Scientific Laboratory (LASL) for the Cross Section Data Library (Dr. R. B. Lazarus). Copies of the ENDF/B Data Files were sent to the National Neutron Cross Section Center at Brookhaven National Laboratory (BNL), in addition to RSIC and the Reactor (K) Division at LASL. At LASL the data will be used by the LAPH code (7) to generate multigroup photon production cross section matrices.

2.6. Translation Codes: LUTE and LATEX

The two codes, LUTE and LATEX, for translation from UK to ENDF/B tormat, are described in detail elsewhere. (6) Briefly, LUTE translates the photon production data insofar as possible, and punches a data-card deck. File I data for ENDF/B, as well as the transition probability arrays, must be punched separately and used as input to LATEX. The LATEX code then reads these input cards along with the LUTE output deck, translates the neutron interaction data, creates a File 3 section for $\overline{\mu_{LAB}}$, and then outputs a

complete ENDF/B tape for the material.

A listing of the translation codes is given in the documentation, $^{(6)}$ and copies of the codes were sent to the Radiation Shielding Information Center at ORNL, to the National Neutron Cross Section Center at BNL, and to the Reactor (K) Division at LASL.

3. Proposed "Physics" And Internal Consistency Checks

3.1. introduction

Due to the difficulty of creating an error-free ENDF/B data set, with its inherent complexity and size, some systematic checking procedures must be devised. Any checking procedure should begin with tests which can be performed by a simple computerized analysis of the data. Only tests which require no interactive capability between the computer and the evaluator are considered here. These tests can be divided into two types. Type I is consistency or format syntax tests similar to those in CHECKER. (9) Some examples of Type I are tests to see that data lie within certain ranges, to see that the proper number of data points are present, and to determine that the data are in proper format. Type II is "physics" checks which will hopefully determine the physical realism and consistency of the data based upon known laws of physics. This type may print out processed data or plots for the program user to check against references or examine visually to detect questionable points. Any inconsistency or suspected error would be flagged by a comment on the output listing. Those checks which were incorporated into the PHOX Code are summarized in §4.

The symbols used in the following section refer to the ENDF/B format for neutron interaction, photon production, and photon interaction data.

3.2. File 3 Checks

Some of the "physics" and consistency checks proposed for File 3 are the following:

- i. $E_1 \ge E_{th}$, the incident neutron energy for a reaction should be greater than or equal to the threshold energy of that reaction. If $E_1 < E_{th}^2$, flag the suspected energy and continue processing. E_{th} is calculated by the formula $E_{th} = (\frac{AWR + 1}{AWR})(-Q)$, for $Q \le 0$. For Q > 0, $E_{th} = 0$.
- 2. Q < 0.0 for MT = 5 thru 14 and 51 thru 80. If Q \geq 0.0, fiag the suspected Q value and attempt to continue processing.

- 3. $10^4 \text{ eV} \le 1 \text{ Q I} \le 2 \times 10^7$ for MT = 5 thru 14 and 51 thru 80. If not in this range, flag the suspected value and continue processing.
- 4. Q = 0.0 for MT = 15 or 110. If not, flag the suspected Q value, set Q = 0.0 and continue processing.
- 5. Q \geq 0.0 for MT = 102. If Q < 0.0, flag the suspected Q value, set Q = 0.0 and continue processing.
- 6. 1.7 \times 10⁶ eV \leq Q \leq 1.2 \times 10⁷ eV for MT = 102 if Q \neq 0.0. If Q is not in this range and \neq 0.0, flag the suspected value, set Q = 0.0, and continue processing.
- 7. For MT = 102, interpolate to find the 2200 m/sec cross section and print it for the user to check against references.
- 8. There is some question as to the proper Q values for the elements. Consider, for example, the materials translated and reviewed for this report. Except for sodium, which is monoisotopic, the other elements have different Q values for their differing isotopes. The proper weighting of the isotopic Q values (e.g. by abundance or product of abundance and 2200 m/sec cross section) is indeterminable. Thus, Q is simply set equal to zero.
- 9. σ = 1.0 for MT = 110. By definition of this reaction type, the cross section must be unity.

3.3. File 14 Checks

Some "physics" and consistency checks that are proposed for File 14 are the following:

- I. LTT should be either I or 2. If not, assume LTT = 2 and attempt to continue processing under the assumption that angular distributions are given as tabulations vice Legendre coefficients.
- 2. LI should be either 0 or 1. If not, assume LI = 0 (i.e., a non-isotropic distribution, and attempt to continue processing).
- 3. NC should be either 0 or 1. If not, assume NC = 0 (i.e., no continuous photon energy spectra are given) and attempt to continue processing.

- 4. If LI = I, test to see that the next card is a SEND card. If not, then set LI = 0 and attempt to continue processing.
- 5. If LTT = 1, then use LEGCK⁽⁹⁾ to test the Legendre coefficients. LEGCK is a computer code that checks Legendre coefficients for possibility and positivity. Any unreasonable or negative coefficients are flagged.
- 6. NE > NR, the number of neutron energy points given must be greater than the number of interpolates. If not, flag the suspected values, set NR = 1, and attempt to continue processing.
- 7. NR > 0. If not, flag the suspected value, set NR = 1 and attempt to continue processing.
- 8. $INT(m) \neq INT(m-1)$. No two consecutive regions should have the same interpolation scheme. If two regions have the same scheme, flag the suspected region and attempt to continue processing.
- 9. ES \geq 0. If ES < 0, flag the suspected value, set ES = 0 and continue processing.
- 10. $EG_{\hat{i}} \leq ES$ when ES > 0. The ith discrete photon energy is less than or equal to the energy of the state excited to produce the photon (when ES > 0). If not, flag the suspected value, set $EG_{\hat{i}} = ES$ and continue processing.
- II. $EG_i > 0$. If not, test that $ES = EG_i = 0$ and NC = i. If this is not the case, flag the suspected value and continue processing.
- 12. ES does not change within any MT number for inelastic scattering to a discrete level. If ES does change, assume ES to have the first value given, flag the inconsistency, and continue processing.
- 13. If ND > 1, the EG $_{\hat{i}}$ must change and must be in decreasing order. If not, flag the suspected values and continue processing.
- 14. ES = |Q| for MT = 5 thru i4 and 5i thru 80. If not, flag the suspected value, set ES = |Q| and continue processing.
- 15. $10^4 \, \text{eV} \leq \text{ES} \leq 2 \times 10^7 \, \text{eV}$ for MT = 5 thru 14 and 51 thru 80. If not, flag the suspected value and continue processing.

3.4. File 15 Checks

Some "physics" and consistency checks that are proposed for File 15 are the following:

- I. The ES values must be the same as in File I4 for a given MT number. If not, flag the suspected value and continue processing.
- 2. All the tests for ES listed in File 14, Section 3.3 also apply in File 15.
- 3. The EG; must have the same values as in File 14 for a given MT number. Under option 2 of File 15 all possible EG; must be determined from the cascade and matched to an EG; in File 14. The existence of a particular value of EG; in File 14 requires a corresponding value in File 15, but not vice versa. If values differ or a File 14 subsection has no correspondent whatsoever in File 15, flag the suspected values and continue processing.
- 4. All the tests for EG $_{\rm i}$ listed in File 14, Section 3.3 also apply in File 15.
- 5. LO should be either 1 or 2. If not, flag the suspected value, set $L_{0}^{0} = 1$ and attempt to continue processing with the assumption that data are given as photon production multiplicities.
- 6. LF should be either I or 2. If not, flag the suspected value, set LF = 2 and attempt to continue processing with the assumption that data are given by discrete photon energies instead of by tabulated distributions.
- 7. NT \leq NS, the number of transitions must be less than or equal to the number of levels below the present level (includes ground state). If not, flag the suspected values, set NT = NS and attempt to continue processing.
- 8. Under option 2, NS = MT 4 for MT = 5 thru I4 and NS = MT 40 for MT = 5I thru 80. If not, flag the suspected value, set NS = MT 4 or MT 40, as appropriate, and continue processing.
 - 9. NR < NP is the same test as listed in File 14, Section 3.3,
- 10. The sum of the probabilities in a cascade should add to unity. If the sum differs from unity by more than 10^{-4} , flag the suspected cascade and continue processing.

For neutron disappearance reactions, in which a compound nucleus is formed, the total energy of the emitted photons, denoted E₊, is less than or equal to the Q value plus the kinetic energy of the neutron, in the center of mass system, denoted E_c. It is assumed that the tabulated neutron energy in the laboratory system is a sufficiently accurate approximation of E_c. If E₊ > (E_c + Q), flag the suspected value and continue processing. This can be calculated by the following:

$$[\overline{E}_{\gamma}(E_{i}) \cdot y_{k}(E_{i}) + \sum_{k}(EG_{i})_{k} \cdot y_{k}(E_{i})] \leq Q + E_{i}^{2}$$

where $\overline{E}_{\gamma} = \int \!\! dE_{\gamma} g(E_{\gamma} + E_{i}) E_{\gamma}$, the $y_{k}(E_{i})$ are the photon multiplicities, and the $g(E_{\gamma} + E_{i})$ are the probability density functions.

- 12. $E_{+} \leq |Q|$ for reactions in which the neutron does not disappear. The total energy of the emitted photons, E_{+} , should be less than or equal to magnitude of the Q value. If $E_{+} > |Q|$, flag the suspected value and continue processing. This is calculated in the same manner as above.
- continue processing. This is calculated in the same manner as above. I3. If Lo = I, Y(E) = $\sum_{k=1}^{Nk} y_k(E)$, the total photon yield should equal the sum of the integrals over the secondary energies. These values should agree to within the fourth significant figure. If not, flag the suspected value and continue processing.
- If $I_1=\int g(E_{\gamma}+E_1^{\epsilon})dE_{\gamma}$, where $g(E_{\gamma}+E_1^{\epsilon})$ is the normalized photon energy distribution (i.e., probability density function), then the normalization is tested by insuring $|I_1-I|\leq 10^{-4}$. If not, flag the suspected normalization value and continue processing.

3.5. File 23 Checks

The proposed "physics" and consistency checks for File 23 are the following:

- I. $\sigma_{\gamma} = \sigma_{pe} + \sigma + \sigma_{c} + \sigma_{pp}$, total photon cross section equals the sum of the individual cross sections for photoelectric effect, Rayleigh or coherent scattering, Compton scattering, and pair production. For practical purposes the effects of the following are neglected: Delbruck or potential scattering, Thomson scattering by the nucleus, photonuclear reactions, and crystal scattering. The sum should agree with σ_{γ} to within the fourth significant figure. If not, flag the suspected value and continue processing.
- 2. The Compton scattering cross section is checked by the Klein-Nishina formula

$$\sigma = \frac{2\pi e^4}{m_0^2 c^4} \left\{ \frac{1+\alpha}{\alpha^2} \left[2 \frac{(1+\alpha)}{1+2\alpha} - \frac{1}{\alpha} \ln(1+2\alpha) \right] + \frac{1}{2\alpha} \ln(1+2\alpha) - \frac{1+3\alpha}{(1+2\alpha)^2} \right\}$$

where α = hv/m_oc² and e = an electron charge. The values should agree to within the second significant figure over most of the energies of practical interest. If not, flag the suspected value and continue processing.

- 3. For pair production $E_i > 1.02$ MeV. If not, flag the suspected value, ignore the corresponding cross section and continue processing.
- 4. For pair production, the total cross section should monotonically increase with photon energy. If not, flag the suspected values and continue processing.
- 5. The energy at which pair production contributes exactly one-half the total cross section is computed, printed and checked by the user against references.
- 6. The energy at which the photoelectric effect contributes exactly one-half the total cross section is computed, printed and checked by user against references.
- 7. The photoelectric effect for each shell has a threshold energy below which the reaction can not take place. Therefore, the lowest energy present in the file is found and printed for checking by the user against references (electron binding energies).
- 8. For the photoelectric effect, the K-edge and all other discontinuities are computed and printed for checking by the user against references.

9. For the photoelectric effect, the cross section decreases monotonically with photon energy at the edges. Any discrepancy would be picked up and flagged as an "edge."

3.6. File 24 Checks

The proposed "physics" and consistency checks for File 24 are the following:

- 1. LTT follows same checks as listed in File 14, Section 3.3.
- 2. LCT should be either I or 2. If not, flag the suspected value, set LCT = I and attempt to continue processing with the assumption that data are given in the LAB system. Where the secondary particle is a photon, the convention adopted $^{(2)}$ is that LCT = i.
- 3. Normalization is tested by the following: $\int_{-1}^{1} d\mu \, p(\mu, E_{\parallel}) = 1$. If the values do not agree to within the fourth significant figure, flag the suspected values and continue processing.

3.7. File 27 Checks

The proposed "physics" and consistency checks for File 27 are the following:

- I. Incoherent form factors (sometimes called incoherent scattering functions) should monotonically increase and approach unity as photon energy increases. They should be within 3% of unity at I MeV.
- 2. Coherent form factors should decrease and approach zero as photon energy increases.

4. PHOX, A "Physics" Checking Code For Photon Data In The ENDF/B Data File

4.1. Introduction and Summary

Much work has been and is being done to place data in the ENDF/B Data File format. In the process of this work there are naturally many errors which occur and which might pass undetected in a visual review of these data. Therefore, a code called CHECKER (9) was written by BNL to check the mechanics (i.e., format syntax) of the data. However, no code existed which checked the physical aspects of the data, or otherwise determined whether the data were reasonable or even possible. Therefore, it is the purpose of this section to explain how several "physics" checks were incorporated into a computer code which does this to some degree for the photon data. The exact division between format syntax and "physics" types of checks is not well defined, so the pragmatic definition of "physics" checks is those checks not done by CHECKER.

There are several types of physical checks which are made by PHOX. They include checks such as testing that the values are within given ranges, that all energy points are above the theoretical threshold as determined from the Q value, that the total energy released by photons does not exceed the energy available as determined by the Q value and neutron energy, etc.

The PHOX code is designed in a manner similar to CHECKER in that it calls various subroutines which do the actual reading, checking and writing. It is written in FORTRAN IV and has been successfully run on the B5500 computer at the University of Virginia.

While the program is designed to attempt to process any section, even if an error in one of the control parameters is discovered, the code may terminate due to trying to read data in an alien format. When control parameters are out of the acceptable range, the code assumes a value within the acceptable range and attempts to proceed. Whenever an error is determined, a message is printed to that effect giving the necessary values, if needed.

4.2. PHOX Code and Subroutines

PHOX is a FORTRAN IV code designed to read an ENDF/B data tape and run certain checks on the data, flagging those it believes to be in error. It is designed primarily to read a BCD card image tape (mode 3) and, while not tested, it is also believed to be able to process a binary tape in standard arrangement for ENDF/B (i.e., mode i). An INDEX'ed listing of PHOX, giving the statement numbers and variable names, is given in Appendix C.

The main program, PHOX, is essentially a calling routine which searches for the files to be checked and assigns the reading, checking, and writing tasks to the appropriate subroutines in the proper order. If the files of interest are not found on the data tape, messages to that effect are written, and the run is terminated. Several of the BNL retrieval subroutines were used in PHOX. These include RREC, TERPI, ERROR, and WREC with its supplemental subroutines. A modification of the CHECKER subroutine TEST2B(MT) was made and incorporated in PHOX. The purpose of this subroutine, called TEST2C(MT), is to check for the proper MT rumbers in File 14.

4.2.1.CKHD(FILE)

CKHD is designed to check the HEAD records of Files 14 and 15. It checks the different fields (not including ZA and AWR) for range, and if discovered to be outside of the range, a "guess" is made and processing continues. When it is necessary to make a guess, a message to that effect is printed which informs the user as to the guessed value.

4.2.2.FIL3(AWR)

FIL3 is designed to calculate a theoretical threshold value for File 3, based on AWR and Q, and to test it against the first energy point given. If this energy point is found to be below the threshold value, a message to that effect is written, along with the theoretical value. FIL3 then stores Q (after checking it for reasonableness of sign and magnitude according to the reaction type) and the larger of either the theoretical threshold or the first energy point, for use in Files 14 and 15.

4.2.3. FILI4(N)

FILI4 is designed to test ES and EG for consistency and reasonableness of magnitude and sign. It also tests for a continuous spectrum and makes sure there is only one continuous spectrum. Using subroutine ESEGPR, FILI4 stores ES and EG for later use.

Each TABI record is tested for increasing order of incident neutron energy and for magnitude as compared with the threshold value stored in FIL3.

4.2.4. FILI5(N)

FILI5 is designed to check either option I or 2. In option I the subsection yields are totaled and checked against the total yields at the total yield energies. The total MeV released per interaction is calculated and compared against the sum of the Q value and kinetic energy, where appropriate. The incident neutron energies and the first energy in each array are checked against the threshold value stored in FIL3. The ES and EG pairs are also used in subroutine ESEGPR.

In option 2 the values of ES $_{\rm i}$ are checked for decreasing order, the TP $_{\rm i}$ for magnitude and total sum, and the GP $_{\rm i}$ for magnitude. The ES's are also checked against the magnitude of Q, as stored in FIL3, and that they correspond to previous state levels. Also the difference between each state level and the previous state levels are checked as ES and EG pairs by ESEGPR.

4.2.5. ESEGPR(N)

ESEGPR is designed to check that each ES-EG pair given in File 14 is used in File 15. In the case of option I in File 15 the comparison is direct, but for option 2 it is necessary to calculate the EG's by substracting the lower state levels from the present state level. After completion of File 15, ESEGPR is called and a final check of all the values, (ES-EG pairs), is made to insure that each has been accounted for. Any that are found to remain unaccounted for are listed on the output.

4.2.6. STATE(LG)

STATE is designed to check that each value of ES $_{j}$ corresponds to a previous value of ES as read from previous inelastic scattering sections, MT = 5-14 and 51-80.

4.3. Input and Output Specifications

4.3.1. PHOX input

The input consists of one ENDF/B data tape, designated unit NT, and two cards. The cards consist of

- 1) NT, MODE, MATW
 - entered in (3IIi) format, where NT is the input tape I/O unit number, MODE is the mode of the input tape, and MATW is the material number of the material to be checked.
- 2) LIST entered in (13A6,A2) tormat. This card is reproduced identically as the first line of output on the listing. This enables the user to place any information he desires on the output.

The card reader is designated as I/0 unit number 5 while the line printer is designated as I/0 unit number 6. The choice of the NT number is left to the user.

4.3.2. PHOX Output

The output consists of a listing of Files 3, i4 and i5 with any comments which PHOX might print. It should be pointed out that all comments are written after the ENDF/B record in which a possible error is detected and not necessarily immediately after the card on which it occurs.

4.4. Burroughs B5500 Computer Fortran IV Complier Features

Only two minor characteristics of the B5500 Fortran IV dialect are known which might affect the running of PHOX on other computers. These are:

- I) Upon entry into a subroutine, the B5500 automatically initializes to zero all variables not held in COMMON. It also initializes all storage points to zero upon entry into the main program.
- 2) The method used on the B5500 to determine the statement to proceed to upon reaching an End-of-File is:

READ (U,F,END=S) LIST

where U is the unit number,

F is the format number,

S is the number of the statement to go to if an End-of-File is reached and

LIST is the list of variables to be read.

APPENDIX A: Corrections and Alterations to the Data in UK Format

The following tabulation lists the card numbers, data changes and comments for all changes made to the data files in UK format since about July 1968. All changes made prior to that date were incorporated into the Cross Section Data Library at LASL, and were mostly to correct cards out of sequence, cards missing and other clerical errors. One alteration which was made after consultation with Drake was to change the RTN for the (n,n'p) reaction from 32 to 28, in agreement with the corresponding ENDF/B reaction type number, MT = 28.

Also found in this appendix, under the heading of A.I.2. are normalization values from File 14 and 15 of SODIUM for the photon secondary distributions as calculated by CHECKER. All materials were affected but only SODIUM is given here as an example. These are integrals found via the trapezoidal rule, as required by the interpolation scheme. They are only noted here; no renormalization was attempted in the UK Data File but corresponding data in ENDF/B were renormalized (cf. MF = 14).

CONTENTS OF APPENDIX A

- A.I. UK Material Number (MIN) 205* SODIUM

 A.I.I. Data File Changes

 A.I.2. Normalization Value from CHECKER
- A.2. UK Material Number (NIN) 206 * MAGNESIUM

 A.2.1. Data File Changes
- A.3. UK Material Number (NIN) 221 * CHLORINE

 A.3.1. Data File Changes
- A.4. UK Material Number (NIN) 227 * POTASSIUM

 A.4.I. Data File Changes
- A.5. UK Material Number (NIN) 231 * CALCIUM

 A.5.1. Data File Changes

A.I. UK Material Number (NIN) 205 * SODIUM

A.I.I. Data File Changes

i.i. bala i i c ona	nges .	
CARD(S) NUMBER:	00010	
CHANGE:	Field 3: From 113	to 105
COMMENTS:	Correct card count.	
CARD(S) NUMBER:	00012, 00013	
CHANGE:	Field 3: From 97	to 89
COMMENTS:	Correct card counts	
CARD(S) NUMBER:	00014	
CHANGE:	Field 3: From 89	to 81
COMMENTS:	Correct card count.	
CARD(S) NUMBER:	00019	
CHANGE:	Field 3: From 81	to · 73
COMMENTS:	Correct card count.	
CARD(S) NUMBER:	00020	
CHANGE:	Field 3: From 57	to 49
COMMENTS:	Correct card count.	
CARD(S) NUMBER:	00022	
CHANGE:	Field 3: From 33	to 25
COMMENTS:	Correct card count.	

CARD(S) NUMBER:	03462
CHANGE:	Field 6 From 5.94301E-1 to 5.75982E-1
COMMENTS:	Error apparent from plot of data.
CARD(S) NUMBER:	03464
CHANGE:	Field 2: From 5.66787E-1 to 6.18222E-1
COMMENTS:	Error
CARD(S) NUMBER:	03479
CHANGE:	Field 2: From 5.68798E-1 to 6.07534E-1
COMMENTS:	Error
CARD(S) NUMBER:	03492
CHANGE:	Field 6: From 4.85219E-1 to 5.22592E-1
COMMENTS:	Error
CARD(S) NUMBER:	03494
CHANGE:	Field <u>2</u> : From <u>5.44224E-1</u> to <u>5.31727E-1</u>
COMMENTS:	Error
CARD(S) NUMBER:	03507
CHANGE:	Field <u>6</u> : From <u>5.04533E-1</u> to <u>5.42012E-1</u>
COMMENTS:	Error
CARD(S) NUMBER:	03784
CHANGE:	Field 6: From 2.95058E-1 to 2.68496E-1
COMMENTS:	Error
CARD(S) NUMBER:	03799
CHANGE:	Field 6: From 3.05212E-1 to 2.68238E-1
COMMENTS:	Error
CARD(S) NUMBER:	03814
CHANGE:	Field 6: From 2.96422E-1 to 2.59656E-1
COMMENTS:	Error

CARD(S) NUMBER:	03938
CHANGE:	Field 6: From 1.70142E-1 to 3.61688E-1
COMMENTS:	Error
CARD(S) NUMBER:	03953
CHANGE:	Field 6: From 1.7185E-1 to 3.62734E-1
COMMENTS:	Error
CARD(S) NUMBER:	03983
CHANGE:	Field 6: From 4.54161E-1 to 3.39764E-1
COMMENTS:	Error
CARD(S) NUMBER:	03998
CHANGE:	Field 6: From 4.81876E-; to 3.29298E-;
COMMENTS:	Error
CARD(S) NUMBER:	03 18
CHANGE:	Field 6: From 3.44406E-1 to 2.95546E-1
COMMENTS:	Error
CARD(S) NUMBER:	03270 (second)
CHANGE:	Field 2: From 3.915:2E-1 to 3.21048E-1
COMMENTS:	Error
CARD(S) NUMBER:	08002
CHANGE:	Field 5: From 69 to 68
COMMENTS:	Clerical error in data pair count.
CARD(S) NUMBER:	i 0002
CHANGE:	Field 5: From 63 to 6:
COMMENTS:	Cierîcai
CARD(S) NUMBER:	12002
CHANGE:	Field 5: From 57 to
COMMENTS:	Clerical
CARD(S) NUMBER:	14002
CHANGE:	Field <u>5</u> : From <u>57</u> to <u>55</u>
COMMENTS:	Clericai

CARD(S) NUMBER:	17001	
CHANGE:	Field 2: From 14	to
COMMENTS:	Correct card count.	
CARD(S) NUMBER:	17010 to 17017 21010 to 21017 23010 to 23017 25010 to 25017 35010 to 35017 37010 to 37017 41010 to 41017	
CHANGE:	Delete these cards.	
COMMENTS:	Neutron angular distribut holds (or essentially at for inelastic scattering Data not meaningful.	threshold for $PCN = 51$)
CARD(S) NUMBER:	21001	
CHANGE:	Field 2: From I2	to II
COMMENTS:	Correct card count.	
CARD(S) NUMBER:	23001	
CHANGE:	Field 2: From 12	to !!
COMMENTS:	Correct card count.	
CARD(S) NUMBER:	25001	
CHANGE:	Field 2: From II	to 10
COMMENTS:	Correct card count.	
CARD(S) NUMBER:	35001	
CHANGE:	Field 2: From 10	to 9
COMMENTS:	Correct card count.	
CARD(S) NUMBER:	37001	
CHANGE:	Field 2: From 7	to 6
COMMENTS:	Correct card count.	
CARD(S) NUMBER:	41001	
CHANGE:	Field 2: From 4	to 3
COMMENTS:	Correct card count.	
CARD(S) NUMBER:	65003	
CHANGE:	Field <u>2</u> : From <u>9.0</u>	to 9.05
COMMENTS:	Clerical error.	

A.1.2. Normalization Value from CHECKER (for Files 14 and 15)

MF = 14 * MT = 5

Energy (MeV)	Normalization Factor	Energy (MeV)	Normalization Factor
0.4580	0.99986	5.0000	0.99984
0. 5000	1.0003	5 .5 000	0.99985
1.0000	0 .9 9981	6.0000	0.99986
1.5000	0.99987	6.5000	0.99987
2.0000	0.99986	7.0000	0.99987
2.5000	0.99986	7.5000	0.99987
3.0000	0.99985	8.0000	0.99987
3.5000	0.99984	8.5000	0.99987
4.0000	0.99983	9.0000	0.99986
4.5000	0.99983		
	<u>MT</u> =	<u>6</u>	
2.1700	0.99920	2.1700	0.99920
2.5000	0.99946	2.5000	0.99946
3.0000	0.99969	3.0000	0.99969
3.5000	0.99987	3.5000	0.99987
4.5000	1.00010	4.5000	1.00010
5.0000	1.00020	5.0000	1.00020
5.5000	0.99960	5.5000	0.99960
6.0000	0.99960	6.0000	0.99960
6.5000	0.99961	6.5000	0.99961
7.0000	0.99962	7.0000	0.99962
7.5000	0.99963	7.5000	0.99963
8.0000	0.99966	8.0000	0.99966
8.5000	0.99968	8.5000	0.99968
9.0000	0.99972	9.0000	0.99972

MT = 9

Energy (MeV)	Normalization Factor	Energy (MeV)	Normalization Factor
2.8230	1.00050	2.8230	1.00210
3.0000	1.00130	3.0000	1.00130
3.5000	1.00060	3.5000	1.00060
4.0000	1.00010	4.0000	1.00010
4.5000	0.99982	4.5000	0.99982
5.0000	0.99970	5.0000	0.99970
5.5000	1.00030	5.5000	1.00030
6.0000	1.00030	6.0000	1.00030
6.5000	1.00030	6.5000	1.00030
7.0000	1.00030	7.0000	1.00030
7.5000	1.00030	7.5000	1.00030
8.0000	1.00040	8.0000	1.00040
8.5000	1.00040	8.5000	1.00040
9.0000	1.00050	9.0000	1.00050
	MT = 10	<u>o</u>	
8.5000	0.99987	8.5000	0.99987
9.0000	0.99982	9.0000	0.99982
	MT = 1	<u>2</u>	
4.0170	0.99966	4.0170	0.99966
4.5000	0.99962	4.5000	0.99962
5.0000	0.99973	5.0000	0.99973
5.5000	0.99981	5.5000	0.99981
6.0000	0.99955	6.0000	0.99955
6.5000	0.99915	6.5000	0.99915
7.0000	0.99896	7.0000	0.99896
7.5000	0.99892	7. 5000	0.99892
8.0000	0.99904	8.0000	0.99904
8.5000	0.99931	8.5000	0.99931
9.0000	0.99974	9.0000	0.99974

MT = 13

Energy (MeV)	Normalization Factor	Energy (MeV)	Normalization Factor
4.0850	0.99972	4.0850	0.99972
4.5000	0.99981	4.5000	0.99981
5.0000	0.99987	5.0000	0.99987
5.5000	0.99975	5.5000	0.99975
6.0000	0.99974	6.0000	0.99974
6.5000	0.99975	6.5000	0.99975
7.0000	0.99963	7.0000	0.99963
7.5000	0.99960	7.5000	0.99960
8.0000	0.99960	8.0000	0.99960
8.5000	0.99965	8.5000	0.99965
9.0000	0.99974	9.0000	0.99974
		MT = 51	
4.9860	0.99961	7. 5000	0.99965
5.5000	0.99968	8.0000	0.99986
6.0000	0.99971	8.5000	1.00030
6.5000	0.99972	9.0000	1.00090
7.0000	0 . 999 7 2	4.9860	0.99961
7.5000	0.99965	5.5000	0.99968
8.0000	0.99986	6.0000	0.99971
8.5000	1.00030	6.5000	0.99972
9.0000	1.00090	7.0000	0.99972
4.9860	0.99961	7.5000	0.99965
5.5000	0.99968	8.0000	0.99986
6.0000	0.99971	8.5000	1.00030
6.5000	0.99972	9.0000	1.00090
7.0000	0 . 999 7 2	4.9860	0.99961
7.5000	0.99965	5.5000	0.99968
8.0000	0.99986	6.0000	0.99971
8.5000	1.00030	6.5000	0.99972
9.0000	1.00090	7.0000	0.99972
4.9860	0.99961	7.5000	0.99965
5.5000	0.99968	8.0000	0.99986
6.0000	0.99971	8.5000	1.00030
6.5000	0.99972	9.0000	1.00090
7.0000	0.99972	34	

MT = 53

Energy (MeV)	Normalization Factor	Energy (MeV)	Normalization Factor
8.5000	0.99978	8.5000	0.99978
9.0000	0.99964	9.0000	0.99964
8.5000	0.99978	8.5000	0.99978
9.0000	0.99964	9.0000	0.99964
	MF = 15	* MT = 15	
9.0500	1.01220		
12.0000	1.00040		
16.0000	an em em em em em em		

A.2. UK Material Number (NIN) 206 * MAGNESIUM

A.2.1.Data File Changes

CARD(S) NUMBER:	00001
CHANGE:	Field 2: From 71650 to 7165
COMMENTS:	Card count changed - clerical error.
CARD(S) NUMBER:	03100
CHANGE:	Field 4: From 2.99689E-1 to 2.45057E-1
COMMENTS:	Error apparent trom plot of data.
CARD(S) NUMBER:	03 48
CHANGE:	Field 3: From -0.1 to -0.55 Field 4: From 0.0 to 0.50028
COMMENTS:	Appears to be an error. Values were interpolated between adjacent pairs in table to get an estimate of the correct value. Zero value in field 4 also occurs in the appendix of NDL-TR-89, Vol. 11.
CARD(S) NUMBER:	03(59 (second time)
CHANGE:	Field <u>2</u> : From <u>4.7732iE-1</u> to <u>4.32770E-i</u>
COMMENTS:	Error
CARD(S) NUMBER:	03200
CHANGE:	Field 4: From 1.38293 to 1.25720
COMMENTS:	Error
CARD(S) NUMBER:	0328i (second time)
CHANGE:	Field 2: From 3.09070E-1 to 2.45343E-1
COMMENTS:	Error
CARD(S) NUMBER:	03429
CHANGE:	Field 1: From <u>-0.0</u> to <u>-0.1</u>
COMMENTS:	Cierical error.
CARD(S) NUMBER:	03455 (second time)
CHANGE:	Field 4: From 1.67767 to 1.46018
COMMENTS:	Error

CARD(S) NUMBER:	15004			
CHANGE:	Field <u>2</u> : From <u>4.32157E-1</u> to <u>5.08099E-1</u>			
COMMENTS:	Error			
CARD(S) NUMBER: CHANGE: COMMENTS:	27098 Field 2: From 4.75 to 4.25 Clerical error.			
CARD(S) NUMBER:				
CHANGE:	Field 2: From 5.5 to 5.0			
COMMENTS:	Clerical error.			
CARD(S) NUMBER:	29003 29011 29019 29027 29035 29043 29052 29061 29070 29079 29088 29097 29107 29117 29127 29137 29147 29157 29168 29179 29190 29201 29212 29223 29235 29247 31003 31013 31023 31033 31044 31055 31066 31077 31088 31099 31111 31123 33003 33013 33023 33033 33043 33053 33063 33074 33085 33096 33107 33118 33129 33141 33153			
CHANGE:	Field 2: From 1.00000-02 to 1.00010-02			
COMMENTS:	Change to avoid double values at 1.00000-02.			
CARD(S) NUMBER:	48001			
CHANGE:	"P" removed from margin.			
COMMENTS:	Clerical or machine error.			
CARD(S) NUMBER:	57018			
CHANGE:	Field <u>4</u> : From <u>5.84000-01</u> to <u>1.96200+00</u>			
COMMENTS:	Clerical error in photon energy.			

A.3. UK Material Number (NIN) 221 * CHLORINE

A.3.1.Data File Changes

CARD(S) NUMBER: 00002 to 1002 CHANGE: Field 5: From 2002 Cierical error in RTN number in the "index". COMMENTS: CARD(S) NUMBER: 09077 Field 4: From 3.11891-01 to 4.85646-01 CHANGE: COMMENTS: Consistency between Q values in File 3, photon energies in File 14, and level energies in File 15. CARD(S) NUMBER: 09079 Field 4: From 3,11891-01 to 4,85646-01 CHANGE: COMMENTS: Consistency.... CARD(S) NUMBER: 09085 Field 4: from 9.88596-01 to 3.86887-01 CHANGE: COMMENTS: Consistency CARD(S) NUMBER: 09087 CHANGE: Field 4: From 9.88596-01 to 3.86887-01 COMMENTS: Consistency CARD(S) NUMBER: 09093 Field 4: From 2.16940+00 to 2.17700-01 CHANGE: COMMENTS: Consistency 09095 CARD(S) NUMBER: Field 4: From 2.16940+00 to 2.17700-01 CHANGE: COMMENTS: Consistency CARD(S) NUMBER: 19002 CHANGE: Field 1: From 74,175 to 4.175 COMMENTS: Energy level in error. A cierical error. CARD(S) NUMBER 2800 i Field 3: From -1.6630+01 to -1.2650+01 CHANGE: COMMENTS: Clerical error in Q value.

CARD(S) NUMBER: 35020 Field 2: From 5.06532-01 to 5.06896-01 CHANGE: COMMENTS: Consistency.... CARD(S) NUMBER: 35024 Field 6: From 5.06532-01 to 5.06896-01 CHANGE: COMMENTS: Consistency.... CARD(S) NUMBER: 35028 Field 2: From 5.10364-01 to 5.10953-01 CHANGE: COMMENTS: Consistency.... CARD(S) NUMBER: 35032 CHANGE: Field 6: From 5.10364-01 to 5.10953-01 COMMENTS: Consistency....

A.4. UK Material Number (NiN) 227 * POTASSIUM

A.4.1. Data File Changes

CARD(S) NUMBER:	03354
CHANGE:	Field 6: From 9.70312-02 to 9.48761-02
COMMENTS:	Error apparent from plot of data.
CARD(S) NUMBER:	03744
CHANGE:	Field 6: From 1.01442-01 to 1.003238-01
COMMENTS:	Error
CARD(S) NUMBER:	03774
CHANGE:	Field 4: From 3.24552+00 to 8.58534-02
COMMENTS:	Error
CARD(S) NUMBER:	03789
CHANGE:	Field 4: From 8.45403+00 to 2.71933-02
COMMENTS:	Error
CARD(S) NUMBER:	03804
CHANGE:	Field 4: From 6.38497+00 to 6.53297-02
COMMENTS:	Error
CARD(S) NUMBER:	03808
CHANGE:	Field 6: From 5.10289-02 to 1.16280-01
COMMENTS:	Error
CARD(S) NUMBER:	03823
CHANGE:	Field 6: From 1.15560-01 to 2.91788-01
COMMENTS:	Error
CARD(S) NUMBER:	03838
CHANGE:	Field 6: From 1.96689-01 to 3.15894-01
COMMENTS:	Error
CARDS:	17070
CHANGE:	Field 6: From Blank to 2)
COMMENTS:	Clerical error - the number of data pairs in the
	subsection.

CARD(S) NUMBER:	27001	
CHANGE:	Field 2: From 60 t	·o <u>6</u>
COMMENTS:	Clerical error.	
CARD(S) NUMBER:	33001	
CHANGE:	Field 2: From blank t	o <u>l</u>
COMMENTS:	Clerical error.	

A.5. UK Material Number (NiN) 23! * CALCIUM

A.5.I. Data File Changes

CARD(S) NUMBER:	0000 i
CHANGE: (a)	Field 2: From 5683 to 5695
(b)	Field 3: From 38 to 39
(C)	Field <u>6</u> : From <u>74</u> to <u>75</u>
COMMENTS: (a)	Change of total number of cards to represent this nuclide including the cards in Section 0.
(b)	Number of card in this index, including this card.
(C)	The number of RTN sections in this material.
CARD(S) NUMBER:	00035
CHANGE:	Field 3: From 95 to 71
COMMENTS:	Number of cards in Section 13015.
CARD(S) NUMBER:	00036
CHANGE:	Field 5: From 13066 to 13060
COMMENTS:	Ciericai Error.
CARD(S) NUMBER:	00039
CHANGE:	ADD card for new section
	Field 1 = 75 Field 2 = 13:03 RTN Field 3 34 number of cards Field 4) Field 5) - blank Field 6)
	Field 7 = 23100039 Material number and sequence number.
CARD(S) NUMBER:	21010
CHANGE:	Field Energy: From 6.0 to 6.2
COMMENTS:	Second neutron energy tabulated is less than the first one in this section. A cierical error.

CARD(S) NUMBER: 26003 CHANGE: Field 3: From 9.001 (MeV) to 9,00010 (MeV) Field 4: From 1.0 -20 to .2387 To eliminate repetition of a zero (i.e., 10^{-20}) COMMENTS: cross section. CARD(S) NUMBER: 39010 CHANGE: Field I: Energy: From 8.0 to 8.2 COMMENTS: Second energy less than first. CARD(S) NUMBER: 43010 CHANGE: Field 1: Energy: From 8.5 to 8.7 COMMENTS: Second neutron energy less than the first. A clerical error. CARD(S) NUMBER: 66001 CHANGE: Field 6: Energy: Changed to 6.56 COMMENTS: Energy level corrected. CARD(S) NUMBER: 67002 CHANGE: (a) Field I: From 6.0 to 9.00010(MeV) Field $\overline{3}$: From $\overline{94}$ to 70 (a) Lower limit of incident neutron energy range COMMENTS: (MeV) changed to correspond with RTN 1015, where lowest energy is 9.0 MeV. (b) Number of cards used to represent this incident neutron energy range, including this card. CARD(S) NUMBER: 67003 thru 67026 CHANGE: Deleted section of data. COMMENTS: These were tabulated energy and cross section data for reactions occurring below threshold. (ref. change on control card numbered 67002) Data can now be found under Reaction Type number 13103. Lower energy limit 9.00010 MeV to avoid duplicate photon specification at

9.0 MeV.

CARD(S) NUM	MBER:	67027
CHANGE:	(a)	Field 2: From iO to 7
	(b)·	-Field <u>3</u> : From <u>9.0</u> to <u>9.00010 (MeV)</u>
COMMENTS:	(a)	Number of sub-sections in the section for this PCN.
	(b)	First energy at which photon production cross sections are specified.
CARD(S) NUM	MBÉR:	67036, 67045, 67055, 67065, 67075, 67085
CHANGE:		Field 2: From io to 7
COMMENTS:		Number of sub-sections in the section for this PCN.
CARD(S) NUM	MBER:	75001 thru 75035
CHANGE:		New section for RTN 13:03: (n,p) reaction.
COMMENTS:		Data were derived from the original cards 67003 thru 67026 with a change only in the sub-section count parameter.

APPENDIX B: Alterations to the Data in Transforming to ENDF/B

As discussed in Section 2.3., several revisions were made to the data for compatibility with the ENDF/B system. These are documented in detail in this Appendix.

CONTENTS OF APPENDIX B

- B.I. ENDF/B Material Number (MAT) 5001 * SODIUM
 B.I.I. Data File Changes
- B.2. ENDF/B Material Number (MAT) 5002 * MAGNESIUM
 B.2.1. Data File Changes
- B.3. ENDF/B Mateial Number (MAT) 5004 * CHLORINE
 B.3.1. Data File Changes
- B.4. ENDF/B Material Number (MAT) 5005 * POTASSIUM
 B.4.1. Data File Changes
- B.5. ENDF/B Material Number (MAT) 5006 * CALCIUM
 B.5.I. Data File Changes

B.I. ENDF/B Material Number (MAT) 5001 * SODIUM

B.I.I. Data File Changes

CARD(S) NUMBER:	695
CHANGE:	Field <u>I</u> : From <u>2.1710E+06</u> to <u>2.1713E+06</u>
COMMENTS:	Threshold altered to make consistent with Q value.
CARD(S) NUMBER:	814
CHANGE:	Field I: From 3.8390E+06 to 3.8395E+06
COMMENTS:	Threshold
CARD(S) NUMBER:	869
CHANGE:	Field I: From 4.6250E+06 to 4.6255E+06
COMMENTS:	Threshold
CARD(S) NUMBER:	913
CHANGE:	Field <u>I</u> : From <u>I.0950E+07</u> to <u>I.0959E+07</u>
COMMENTS:	Threshold
CARD(S) NUMBER:	955
CHANGE:	Field 2: From <u>-0.620E+7</u> to <u>-0.627E+7</u>
COMMENTS:	Consistency between Q values in File 3, photon energies in File 14, and level energies in File 15.
CARD(S) NUMBER:	966
CHANGE:	Field I: From 7.4220E+06 to 7.4221E+06
COMMENTS:	Threshold
CARD(S) NUMBER:	977
CHANGE:	Field 2: From 0.0 to +6.959E+6
COMMENTS:	Enter Q value for (n,γ) reaction in MF = 3, MT = 102. (Na is monoisotropic 23 Na).
CARD(S) NUMBER:	5370
CHANGE:	Field 2: From 2.1700E+06 to 2.1713E+06
COMMENTS:	Threshold

CARD(S) NUMBER:	5505
CHANGE:	Field 2: From 1.6400E+6 to 1.6408E+6
COMMENTS:	Consistency between Q values in File 3, photon energies in File 14, and level energies in File 15.
CARD(S) NUMBER:	5507
CHANGE:	Field 2: From 2.1700E+06 to 2.1713E+06
COMMENTS:	Threshold
CARD(S) NUMBER:	5650, 5778
CHANGE:	Field 2: From 2.8230E+06 to 2.8240E+06
COMMENTS:	Threshold
CARD(S) NUMBER:	5908, 6027
CHANGE:	Field <u>2</u> : From <u>3.1140E+06</u> to <u>3.1150E+06</u>
COMMENTS:	Threshold
CARD(S) NUMBER:	6148, 6258, 6368, 6478
CHANGE:	Field 2: From 3.8380E+06 to 3.8395E+06
COMMENTS:	Threshold
CARD(S) NUMBER:	6590, 6691
CHANGE:	Field <u>2</u> : From <u>4.0170E+06</u> to <u>4.0190E+06</u>
COMMENTS:	Threshold
CARD(S) NUMBER:	6794, 6895, 7249, 7332
CHANGE:	Field <u>2</u> : From <u>4.0850E+06</u> to <u>4.0870E+06</u>
COMMENTS:	Threshold
CARD(S) NUMBER:	7000, 7083, 7166
CHANGE:	Field <u>2</u> : From <u>4.9860E+06</u> to <u>4.9880E+06</u>
COMMENTS:	Threshold
CARD(S) NUMBER:	7419, 7457, 7495, 7533
CHANGE:	Field 2: From 7.4220E+06 to 7.4221E+06
COMMENTS:	Threshold

CARD(S) NUMBER:	7579
CHANGE:	Field 2: From 0.23 to 0.33
COMMENTS:	To correct error in Fig. 1 of Volume 2, (NDL-TR-89, Part II,GA-7829); transition probability array, 3rd level, as referenced in Fig. 1.
CARD(S) NUMBER:	7625
CHANGE:	Field 1: From 9.00E+6 to 9.05E+6
COMMENTS:	To agree with MF = 3, MT = 15 where cross section is essentially zero until 9.05 MeV.
CARD(S) NUMBER:	7839
CHANGE:	Field <u>2</u> : From <u>1.6400E+6</u> to <u>1.6408E+6</u>
COMMENTS:	Consistency
CARD(S) NUMBER:	7851
CHANGE:	Field <u>2</u> : From <u>1.9520E+6</u> to <u>1.9518E+6</u>
COMMENTS:	Consistency
CARD(S) NUMBER:	7863
CHANGE:	Field <u>2</u> : From <u>2.2660E+6</u> to <u>2.2658E+6</u>
COMMENTS:	Consistency
CARD(S) NUMBER:	7881
CHANGE:	Field <u>2</u> : From <u>2.5450E+6</u> to <u>2.5448E+6</u>
COMMENTS:	Consistency
CARD(S) NUMBER:	7893
CHANGE:	Field <u>2</u> : From <u>3.2390E+6</u> to <u>3.2388E+6</u>
COMMENTS:	Consistency
CARD(S) NUMBER:	7929
CHANGE:	Field <u>2</u> : From <u>3.4760E+6</u> to <u>3.4758E+6</u>
COMMENTS:	Consistency
CARD(S) NUMBER:	7947
CHANGE:	Field 2: From 4.3390E+6 to 4.3388E+6
COMMENTS:	Consistency

CARD(S) NUMBER: 7971

CHANGE: Field 2: From 3.8800E+6 to 3.8790E+6

COMMENTS: Consistency...

B.2. ENDF/B Material Number (MAT) 5002 * MAGNESIUM

B.2.I. Data File Changes

CARD(S) NUMBER:	888, 1046
CHANGE:	Field <u>I</u> : From <u>6.0760E+05</u> to <u>6.0823E+05</u>
COMMENTS:	Threshold altered to make consistent with Q value.
CARD(S) NUMBER:	1099
CHANGE:	Field 1: From 1.0150E+06 to 1.0165E+06
COMMENTS:	Consistency between level energies (or Q values) in Files 3, 14, and 15.
CARD(S) NUMBER:	44
CHANGE:	Field 2: From -1.3678E+06 to -1.3680E+06
COMMENTS:	Threshold
CARD(S) NUMBER:	1229
CHANGE:	Field <u>I</u> : From <u>I.6760E+6</u> to <u>I.6779E+6</u>
COMMENTS:	Threshold
CARD(S) NUMBER:	1265
CHANGE:	Field <u>I</u> : From <u>I.8800E+6</u> to <u>I.885IE+6</u>
COMMENTS:	Threshold
CARD(S) NUMBER:	1297
CHANGE:	Field <u>I</u> : From <u>2.0400E+6</u> to <u>2.0434E+6</u>
COMMENTS:	Threshold
CARD(S) NUMBER:	1326
CHANGE:	Field <u>I</u> : From <u>2.6690E+6</u> to <u>2.6715E+6</u>
COMMENTS:	Threshold
CARD(S) NUMBER:	1345
CHANGE:	Field <u>1</u> : From <u>2.8470E+6</u> to <u>2.8496E+6</u>
COMMENTS:	Threshold
CARD(S) NUMBER:	1361
CHANGE:	Field <u>I</u> : From 2.9160E+6 to 2.9193E+6
COMMENTS:	Threshold

CARD(S) NUMBER:	1376	
CHANGE:	Field I: From 3.0530E+6	to 3.0620E+6
COMMENTS:	Threshold	
CARD(S) NUMBER:	1450	
CHANGE:	Field 1: From 7.6200E+6	to 7.6279E+6
COMMENTS:	Threshold	
CARD(S) NUMBER:	1518	
CHANGE:	Field 2: From -4.23E+06	to -4.232E+06
COMMENTS:	Consistency	
CARD(S) NUMBER:	1564	
CHANGE:	Field 2: From -5.22E+06	
COMMENTS:	Consistency	
CARD(S) NUMBER:	1566	
CHANGE:	Field <u>I:</u> From <u>5.4400E+6</u>	to 5.4408E+6
COMMENTS:	Threshold	
CARD(S) NUMBER:	6686	
CARD(S) NUMBER: CHANGE:	6686 Field 2: From 1.0150E+6	
	Field 2: From 1.0150E+6	
CHANGE:	Field 2: From 1.0150E+6	to 1,0165E+6
CHANGE: COMMENTS:	Field 2: From 1.0150E+6 Threshold	to 1.0165E+6
CHANGE: COMMENTS: CARD(S) NUMBER:	Field 2: From 1.0150E+6 Threshold	to 1.6779E+6
CHANGE: COMMENTS: CARD(S) NUMBER: CHANGE:	Field 2: From 1.0150E+6 Threshold 6991 Field 2: From 1.6760E+6	to 1.6779E+6
CHANGE: COMMENTS: CARD(S) NUMBER: CHANGE: COMMENTS:	Field 2: From 1.0150E+6 Threshold 6991 Field 2: From 1.6760E+6 Threshold	to 1.0165E+6 to 1.6779E+6
CHANGE: COMMENTS: CARD(S) NUMBER: CHANGE: COMMENTS: CARD(S) NUMBER:	Field 2: From 1.0150E+6 Threshold 6991 Field 2: From 1.6760E+6 Threshold 7058	to 1.0165E+6 to 1.6779E+6
CHANGE: COMMENTS: CARD(S) NUMBER: CHANGE: COMMENTS: CARD(S) NUMBER: CHANGE:	Field 2: From 1.0150E+6 Threshold 6991 Field 2: From 1.6760E+6 Threshold 7058 Field 2: From 1.8800E+6	to 1.0165E+6 to 1.6779E+6
CHANGE: COMMENTS: CARD(S) NUMBER: CHANGE: COMMENTS: CARD(S) NUMBER: CHANGE: COMMENTS:	Field 2: From 1.0150E+6 Threshold 6991 Field 2: From 1.6760E+6 Threshold 7058 Field 2: From 1.8800E+6 Threshold	to 1.0165E+6 to 1.6779E+6 to 1.8851E+6
CHANGE: COMMENTS: CARD(S) NUMBER: CHANGE: COMMENTS: CARD(S) NUMBER: CHANGE: COMMENTS: CARD(S) NUMBER:	Field 2: From 1.0150E+6 Threshold 6991 Field 2: From 1.6760E+6 Threshold 7058 Field 2: From 1.8800E+6 Threshold 7116	to 1.0165E+6 to 1.6779E+6 to 1.8851E+6
CHANGE: COMMENTS: CARD(S) NUMBER: CHANGE: COMMENTS: CARD(S) NUMBER: CHANGE: COMMENTS: CARD(S) NUMBER: CHANGE: COMMENTS:	Field 2: From 1.0150E+6 Threshold 6991 Field 2: From 1.6760E+6 Threshold 7058 Field 2: From 1.8800E+6 Threshold 7116 Field 2: From 2.0400E+6	to 1.0165E+6 to 1.6779E+6 to 1.8851E+6
CHANGE: COMMENTS: CARD(S) NUMBER: CHANGE: COMMENTS: CARD(S) NUMBER: CHANGE: COMMENTS: CARD(S) NUMBER: CHANGE: COMMENTS: CARD(S) NUMBER: CHANGE: COMMENTS:	Field 2: From 1.0150E+6 Threshold 6991 Field 2: From 1.6760E+6 Threshold 7058 Field 2: From 1.8800E+6 Threshold 7116 Field 2: From 2.0400E+6 Threshold	to 1.0165E+6 to 1.8851E+6 to 2.0434E+6

CARD(S) NUMBER:	7 94	
CHANGE:	Field 2: From 3.0530E+6	to 3.0620E+6
COMMENTS:	Threshold	
CARD(S) NUMBER:	7223	
CHANGE':	Field 2: From 2.735E+06	to 2.752E+06
COMMENTS:	Consistency	
CARD(S) NUMBER:	7202	
CHANGE:	Field 2: From 4.4080E+6	
COMMENTS:	Threshold	
CARD(S) NUMBER:	7357	
CHANGE:	Field <u>2</u> : From <u>4.4080E+6</u>	to 4.410E+6
COMMENTS:	Threshold	
CARD(S) NUMBER:	7424	
CHANGE:	Field 2: From 5.44000+6	to 5.4408E+6
COMMENTS:	Threshold	
CARD(S) NUMBER:	7471	
CHANGE:	Field 2: From 4.6370E+06	to 4.6320E+06
COMMENTS:	Consistency	
CARD(S) NUMBER:	7513	
CARD(S) NUMBER: CHANGE:	7513 Field <u>I</u> : From <u>I.3676E+07</u>	to 1.3680E+06
		to 1.3680E+06
CHANGE:	Field <u>I</u> : From <u>I.3676E+07</u>	to <u>1.3680E+06</u>
CHANGE: COMMENTS:	Field <u>l</u> : From <u>1.3676E+07</u> Consistency	
CHANGE: COMMENTS: CARD(S) NUMBER:	Field <u>l</u> : From <u>l.3676E+07</u> Consistency 7530, 7534, 7538	to <u>0.0</u>
CHANGE: COMMENTS: CARD(S) NUMBER: CHANGE:	Field <u>l</u> : From <u>l.3676E+07</u> Consistency 7530, 7534, 7538 Field <u>2</u> : From <u>l.0</u>	to <u>0.0</u>
CHANGE: COMMENTS: CARD(S) NUMBER: CHANGE: COMMENTS:	Field <u>l</u> : From <u>l.3676E+07</u> Consistency 7530, 7534, 7538 Field <u>2</u> : From <u>l.0</u> cf. Section 2.3.2. of text	to <u>0.0</u>
CHANGE: COMMENTS: CARD(S) NUMBER: CHANGE: COMMENTS: CARD(S) NUMBER:	Field I: From 1.3676E+07 Consistency 7530, 7534, 7538 Field 2: From 1.0 cf. Section 2.3.2. of text	to 0.0 . to 4.1260E+6
CHANGE: COMMENTS: CARD(S) NUMBER: CHANGE: COMMENTS: CARD(S) NUMBER: CHANGE:	Field <u>l</u> : From <u>l.3676E+07</u> Consistency 7530, 7534, 7538 Field <u>2</u> : From <u>l.0</u> cf. Section 2.3.2. of text 7617 Field <u>l</u> : From <u>4.1203E+06</u>	to 0.0 . to 4.1260E+6
CHANGE: COMMENTS: CARD(S) NUMBER: CHANGE: COMMENTS: CARD(S) NUMBER: CHANGE: CHANGE: COMMENTS:	Field 1: From 1.3676E+07 Consistency 7530, 7534, 7538 Field 2: From 1.0 cf. Section 2.3.2. of text 7617 Field 1: From 4.1203E+06 Consistency	to <u>0.0</u> . to <u>4.1260E+6</u>

CARD(S) NUMBER:	7621
CHANGE:	Field 1: From 4.2300E+06 to 4.2320E+06
COMMENTS:	Consistency
CARD(S) NUMBER:	7622
CHANGE:	Field 1: From 1.3676E+06 to 1.3680E+06
COMMENTS:	Consistency
CARD(S) NUMBER:	7625
CHANGE:	Field I: From 5.2200E+06 to 5.2240E+06
COMMENTS:	Consistency
CARD(S) NUMBER:	7626
CHANGE:	Field :: From 1.3676E+06 to 1.3680E+06
COMMENTS:	Consistency
CARD(S) NUMBER:	7630
CHANGE:	Field 1: From 4.2306E+06 to 4.2320E+6
	Field 3: From 4.1203E+06 to 4.1200E+6 Field 5: From 1.3676E+06 to 1.3680E+6
COMMENTS:	Consistency
CARD(S) NUMBER:	7634
CHANGE:	Field <u>1</u> : From 4,2300E+06 to 4,2320E+06
	Field 2: From 1.3676E+06 to 1.3680E+06
COMMENTS:	Consistency
CARD(S) NUMBER:	7778
CHANGE:	Field 2: From $2.7350E+06$ to $2.7520E+06$
COMMENTS:	Consistency
CARD(S) NUMBER:	7806
CHANGE:	Field 2: From 4.6370E+06 to 4.6320E+06
COMMENTS:	Consistency
CARD(S) NUMBER:	7813
CHANGE:	Field 2: From 2.2100E+06 to 2.2080E+06
COMMENTS:	Consistency

CARD(S) NUMBER: 7818

CHANGE: Field 2: From 5.0700E+06 to 5.0720E+06

COMMENTS: Consistency....

B.3. ENDF/B Material Number (MAT) 5004 * CHLORINE

B.3.1. Data File Changes

CARD(S) NUMBER: 1278 Field 2: From -1.6630E+07 to -0.1265E+08 CHANGE: COMMENTS: Threshold altered to make consistent with Q Value. CARD(S) NUMBER: 1302 Field 1: From 6.5500E+06 to 6.5512E+06 CHANGE: COMMENTS: Threshold... CARD(S) NUMBER: i329 Field 1: From 6.2720E+06 to -6.2736E+06 CHANGE: COMMENTS: Threshoid... CARD(S) NUMBER: 6451, 6452, 6453, 6454, 6455 CHANGE: Deleted. COMMENTS: MF = i4, MT = 52, 53, 54 Combined and changed to MF = 14, MT = 110. CARD(S) NUMBER: 6488 Field i: From 0.0 CHANGE: to 1,22E+06 COMMENTS: Clerical Error. - CARD(S) NUMBER: Sections created using UK Data from RTN numbers 13052, 13053, 13054 Excitation of first 3 levels of ³⁷Cl were entered CCMMENTS: in MT = 110 as photon production cross sections starting_at E = 0.0. Other levels (MT = 5-14, 51) are for 35Ci. (Cf. Sec. 2.2.1).

B.4. ENDF/B Material Number (MAT) 5005 * POTASSIUM

B.4.1. Data File Changes

CARD(S) NUMBER: 956

CHANGE:

Field 1: From 2.5910E+06 to 2.5912E+06

COMMENTS:

Threshold altered to be consistent with Q value

CARD(S) NUMBER: 1201

CHANGE:

Field <u>l</u>: From 6.3700E+06 to 6.3702E+06

COMMENTS:

Threshold....

CARD(S) NUMBER: 5570

CHANGE:

Field 2: From 3.0990E+06 to 3.1000E+06

COMMENTS:

Threshold....

B.5. ENDF/B Material Number (MAT) 5006 * CALCIUM

B.5.1. Data File Changes

CARD(S) NUMBER:	1054
CHANGE:	Field 1: From 1.18700E+06 to 1.1872E+06
COMMENTS:	Threshold aitered to make consistent with Q value.
CARD(S) NUMBER:	1134
CHANGE:	Field i: From 1,1870E+06 to 1,1872E+06
COMMENTS:	Threshold
CARD(S) NUMBER:	1162
CHANGE:	Field 1: From 3.4300E+06 to 3.4344E+06
COMMENTS:	Threshold
CARD(S) NUMBER:	1236
CHANGE:	Field 1: From 4.5900E+06 to 4.5928E+06
COMMENTS:	Threshold
CARD(S) NUMBER:	i 250
CHANGE:	Field <u>i</u> : From 5.4000E+06 to 5.4027E+06
COMMENTS:	Threshold
CARD(S) NUMBER:	1262
CHANGE:	Field 1: From 5.7600E+06 to 5.7615E+06
COMMENTS:	Threshold
CARD(S) NUMBER:	1292
CHANGE:	Field <u>1</u> : From 6.7200E+06 to 6.725 E+06
COMMENTS:	<u>Threshold</u>
CARD(S) NUMBER:	1313
CHANGE:	Field 1: From 1.028E+07 to 1.0283E+07
COMMENTS:	Threshold
CARD(S) NUMBER:	1374
CHANGE:	Field <u>i</u> : From 8.2900E+06 to 8.2936E+06
COMMENTS:	Threshold

CARD(S) NUMBER:	1382
CHANGE:	Field 1: From 8.5800E+06 to 8.5807E+06
COMMENTS:	Threshold
CARD(S) NUMBER:	5120
CHANGE:	Field 2: From 3.8240E+06 to 3.8300E+06
COMMENTS:	Threshold
CARD(S) NUMBER:	5521
CHANGE:	Field <u>2</u> : From <u>5.4000E+06</u> to <u>5.4027E+06</u>
COMMENTS:	Threshold
CARD(S) NUMBER:	5604
CHANGE:	Field <u>2</u> : From <u>5.4000E+06</u> to <u>5.4027E+06</u>
COMMENTS:	Threshold
CARD(S) NUMBER:	5689
CHANGE:	Field 2: From 5.7600E+06 to 5.76+5E+06
COMMENTS:	Threshold
CARD(S) NUMBER:	5763
CHANGE:	Field <u>6</u> : From <u>8</u> to <u>7</u>
COMMENTS:	Clerical error
CARD(S) NUMBER:	5764
CHANGE:	Field <u>I</u> : From <u>8</u> to <u>7</u>
COMMENTS:	Clerical error.
CARD(S) NUMBER:	5973
CHANGE:	Field <u>2</u> : From <u>6.7200E+06</u> to <u>6.7251E+06</u>
COMMENTS:	Threshold
CARD(S) NUMBER:	6029
CHANGE:	Field <u>2</u> : From <u>6.7200E+06</u> to <u>6.7251E+06</u>
COMMENTS:	Threshold
CARD(S) NUMBER:	MF = 14 MT = 15
CHANGE:	Added section
COMMENTS:	Add isotropic distribution for photons, both discrete and continuum, from (n,p) reactions. Con-
	tinuum photons from RTN 13015 (cf. section 2.2.3).

APPENDIX C: INDEX'ed Listing of PHOX

The following INDEX'ed listing of PHOX contains only the portions of the code which were written at the University of Virginia and does not include the standard ENDF/B retrieval subroutines distributed by the NNCSC. The INDEX'ed listing includes both the statement numbers and variable names.

```
INDEX
                                                                                        PAGE
                                                                                                2
             *********
   12
                 TEND = 1
                                                                                        PHX
                                                                                              51
                                                                                        PHX
                                                                                             52
                 TPID = 6
   13
                                                                                        PHX
                                                                                              53
          C
          Č
                                                                                        PHX
                                                                                              54
                                                                                        PHX
                                                                                              55
   14
                 DIMENSION A(14)
                 COMMON/COUN/LG, NC, ND, NE, NI, NK, NP, NTAB, NS1
                                                                                        PHX
                                                                                              56
   15
                 COMMON/RECS/MAT, MF, MT, C1, C2, L1, L2, N1, N2, NBT(100), JNT(100), X(2000), PHX
                                                                                             57
   16
                1
                              Y(2000),B(2000);N1X,N2X,NS
                                                                                        PHX
                                                                                             58
                                                                                             59
                                                                                        PHX
   17
                 N1X = 100
                 N2X = 2000
                                                                                        PHX
                                                                                              60
   18
                                                                                        PHX
          C
                                                                                             61
          C----READ INPUT.
                                                                                        PHX
                                                                                             62
                                                                                        PHX
          C
                                                                                             63
                READ (5,601,END=18) NT,MODE,MATW
                                                                                        PHX
   19
                                                                                             64
                READ (5,602,END=18) (4(I),I=1,14)
   20
                                                                                        PHX
                                                                                             65
                                                                                        PHX
  21
                WRITE (6,603) (A(I), I=1,14)
                                                                                             66
          C
                                                                                        PHX
                                                                                             67
          C-===SEARCH FOR FILE 3.
                                                                                        PHX
                                                                                             68
          C _
                                                                                        PHX
                                                                                             69
                CALL SEARCH(NT, MUDE, MATW, 3, 0, LNT)
  22
                                                                                        PHX
                                                                                             70
  23
                BACKSPACE NT
                                                                                        PHX
                                                                                             71
                READ (NT, 604) NS
                                                                                        PHX
  24
                                                                                             72
                IM (LNT .EQ. 0) GO TO 2
  25
                                                                                        PHX.
                                                                                             7.3
                G0 TO 19
                                                                                        PHX
  26
                                                                                             74
          C
                                                                                        PHX
                                                                                             75
                                                                                        PHX
          C----RROCESS FILE 3.
                                                                                             76
          C
                                                                                        PHX
                                                                                             77
  27
              1 CALL RREC(HEAD, NT, MODE, =1.0)
                                                                                        PHX
                                                                                             78
              2 CALL WRECCHEAD, 6, BCD)
                                                                                        PHX
                                                                                             79
  28
  29
                IF (MF .EQ. 0) GO TO 3
                                                                                        PHX
                                                                                             80
                ANR = C2
  30
                                                                                        PHX
                                                                                             81
                                                                                        PHX
  31
                CALL RREC(TAB1, NT, MODE, =1.0)
                                                                                             82
                CALL WREC(TAB1,6,8CD)
  32
                                                                                        PHX
                                                                                             83
                                                                                        PHX
  33
                CALL FIL3(AWR)
                                                                                             84
                CALL RREC(SEND, NT, MODE, =1.0)
  34
                                                                                        PHX
                                                                                             85
  35
                CALL WREC(SEND, 6, BCD)
                                                                                        PHX
                                                                                             86
                GU TO 1
                                                                                        PHX
                                                                                             87
  36
          С
                                                                                        PHX
                                                                                             88
          C----SEARCH FOR FILE 14.
                                                                                        PHX
                                                                                             89
          C
                                                                                        PHX
                                                                                             90
              3 CALL SEARCH(NT, MUDE, MATW, 14, 0, LNT)
  37
                                                                                        PHX
                                                                                             91
                BACKSPACE NI
                                                                                        PHX
                                                                                             92
  38
                READ (NT, 604) NS
                                                                                        PHX
  39
                                                                                             93
                IF (LNT .EQ. 0) GO TO 5
                                                                                             94
  40
                                                                                        PHX
  41
                GØ TO 20
                                                                                        PHX
                                                                                             95
                                                                                        PHX
                                                                                             96
          C
          C----PROCESS FILE 14.
                                                                                        PHX
                                                                                             97
          C
                                                                                        PHX
                                                                                             98
              4 CALL RREC(HEAD, NI, MODE, -1.0)
  42
                                                                                        PHX
                                                                                             99
              5 CALL WREC(HEAD, 6, BCD)
  43
                                                                                        PHX 100
```

```
INDEX
                                                                                       PAGE
                                                                                               3
            ***********
   44
                IF (MF .EQ. 0) GO TO 12
                                                                                       PHX 101
                CALL CKHD(MF)
   45
                                                                                       PHX 102
                                                                                       PHX 103
   46
                 CALL TEST2C(MT)
                 IF (L1 .EQ. 1) GO TO §
                                                                                       PHX 104
   47
                 IF (L2 .EQ. 1) GU TU 9
                                                                                       PHX 105
   48
          C
                                                                                       PHX 106
          C
                TABULATED FORM
                                                                                       PHX 107
                                                                                       PHX 108
          C
   49
                NTA = ND + NC
                                                                                       PHX 109
                DU 7 J = 1, NTA
   50
                                                                                       PHX 110
                CALL RREC(TAB2,NT,MODE,=1.0)
                                                                                       PHX 111
   51
                CALL WRECCTAB2,6,8CD)
                                                                                       PHX 112
   52
   53
                 CALL FIL14(1)
                                                                                       PHX 113
                DO 6 I = 1, NE
CALL RREC(TAB1,NT,MODE,-1.0)
                                                                                       PHX 114
   54
   55
                                                                                       PHX 115
                CALL WREC(TAB1, 6, BCD)
                                                                                       PHX 116
   56
              6 CALL FIL14(2)
                                                                                       PHX 117
   57
   58
                CALL FIL14(3)
                                                                                       PHX 118
                                                                                       PHX 119
              8 CALL RREC(SEND, NT, MODE, -1.0)
   59
   60
                CALL WREC(SEND, 6, BCD)
                                                                                       PHX 120
   61
                GU TO 4
                                                                                       PHX 121
                                                                                       PHX 122
          C
                LEGENDRE PULYNOMIAL FORM
                                                                                       PHX 123
          C
                                                                                       PHX 124
              9 \text{ NTA} = \text{ND} + \text{NC}
                                                                                       PHX 125
   62
                00 11 J. = 1, NTA
                                                                                       PHX 126
   63
                CALL RREC(TAB2.NT, MUDE, ~1.0)
                                                                                       PHX 127
   64
                CALL WREC(TAB2,6,BCD)
   65
                                                                                       PHX 128
                                                                                       PHX 129
   66
                CALL FIL14(4)
                                                                                       PHX 130
   67
                DH 10 I = 1, NE
                CALL RREC(LIST, NT, MODE, -1.0)
                                                                                       PHX 131
   68
   69
                CALL WREC(LIST, 6, BCD)
                                                                                       PHX 132
   70
             10 CALL FIL14(5)
                                                                                       PHX 133
             11 CALL FIL14(6)
                                                                                       PHX 134
   71
                CALL RREC(SEND, NT, MUDE, -1.0)
   72
                                                                                       PHX 135
                GALL WREC(SEND, 6, BCD)
                                                                                       PHX 136
   73
   74
                GU TO 4
                                                                                       PHX 137
                                                                                       PHX 138
          C
          C---PROCESS FILE 15.
                                                                                       PHX 139
                                                                                       PHX 140
             12 CALL RREC(HEAD, NT, MODE, -1.0)
   75
                                                                                       PHX 141
                CALL WREC (HEAD, 6, BCD)
                                                                                       PHX 142
   76
   77
                IF (MF .EQ. 0) GO TO 17
                                                                                       PHX 143
                CALL CKHD(MF)
                                                                                       PHX 144
   78
                IF (L1 .EQ. 2) GO TO 16
   79
                                                                                       PHX 145
          C
                                                                                       PHX 146
                                                                                       PHX 147
          C
                OPTION 1
                                                                                       PHX 148
          C
                CALL RREC(TAB1, NT, MODE, -1.0)
                                                                                       PHX 149
   80
                CALL WRECCTAB1,6,BCD)
                                                                                       PHX 150
   81
```

```
INDEX
                                                                                     PAGE
                                                                                             4
            *****************
  82
                CALL FIL15(1)
                                                                                     PHX 151
                                                                                     PHX 152
  83
                DO 15 J = 1, NK
                CALL RREC(TAB1,NT,MODE,-1.0)
                                                                                     PHX 153
  84
  85
                CALL WREC(TABI, 6, BCD)
                                                                                     PHX 154
  85
                IF (L2 .EQ. 2) GU TO 14
                                                                                     PHX 155
                                                                                     PHX 156
          C
          C
                AMBITRARY TABULATED FUNCTION
                                                                                     PHX 157
                                                                                     PHX 158
          C
  87
                                                                                     PHX 159
                CALL FIL15(2)
  88
                CALL RREC(TAB2, NT, MODE, =1.0)
                                                                                     PHX 160
                CALL WREC(TAB2,6,BCD)
  89
                                                                                     PHX 161
                CALL FIL15(3)
                                                                                     PHX 162
  90
  91
                DO 13 I = 1, NE
                                                                                     PHX 163
                CALL RRECCTABI, NT, MODE, =1.0)
  92
                                                                                     PHX 164
  93
                CALL WREC(TAB1,6,BCD)
                                                                                     PHX 165
  94
                                                                                     PHX 166
             13 CALL FIL15(4)
  95
                CALL FIL15(5)
                                                                                     PHX 167
  96
                G0 TO 15
                                                                                     PHX 168
                                                                                     PHX 169
         C
                DISCRETE FINAL ENERGY
                                                                                     PHX 170
         C
         C
                                                                                     PHX 171
  97
             14 CALL FIL15(6)
                                                                                     PHX 172
                                                                                     PHX 173
  98
             15 CUNTINUE
                                                                                     PHX 174
  99
                CALL FIL15(7)
 100
                CALL RREC(SEND, NT, MUDE, -1.0)
                                                                                     PHX 175
 101
                CALL WREC(SENU, 6, BCD)
                                                                                     PHX 176
 102
                GU TO 12
                                                                                     PHX 177
         C
                                                                                     PHX 178
         C
                                                                                     PHX 179
                S NOITED
                                                                                     PHX 180
 103
             16 CALL RREC(LIST, NT, MDDE, -1.0)
                                                                                     PHX 181
 104
                CALL WREC(LIST, 6, BCO)
                                                                                     PHX 182
 105
                CALL FIL15(8)
                                                                                     PHX 183
 106
                CALL RREC(SEND, NT, MODE, -1.0)
                                                                                     PHX 184
 107
                CALL WREC(SEND, 6, BCD)
                                                                                     PHX 185
 108
                GO TO 12
                                                                                     PHX 186
                                                                                     PHX 187
 109
             17 CALL ESEGPR(5)
 110
                SIDP
                                                                                     PHX 188
             18 WRITE (6,605)
 111
                                                                                     PHX 189
                                                                                     PHX 190
 112
                STOP
             19 WRITE (6,606) NT, MUDE, MATW
 113
                                                                                     PHX 191
                                                                                     PHX 192
 114
                STOP
 115
             20 WRITE (6,607)
                                                                                     PHX 193
 116
                STOP
                                                                                     PHX 194
           601 FURMAT (3111)
 117
                                                                                     PHX 195
           602 FORMAT (13A6, A2)
                                                                                     PHX 196
 118
 119
           6U3 FURMAT (1X, 13A6, A2//)
                                                                                     PHX 197
 120
           604 FORMAT (75X,15)
                                                                                     PHX 198
 121
           605 FORMAR (15(1H*), 16H NO CARD INPUT. ,79(1H*))
                                                                                     PHX 199
 122
           046 FURMAT (15(1H*),19H FILE 3 NOT FOUND, ,6H NT = ,12,8H MODE = ,11,7PHX 200
```

INDEX	************	PAGE 5
	1H MAT = ,14,51(1H+))	PHX 201
123	607 FORMAT (1H1,14(1H*),20H FILE 14 NOT FOUND, ,75(1H*))	PHX 202
124	END	PHX 203-

INDE	. х									1	PAGE 6
		*****	*****			****		*****	*****	***	
SYMBOL		= = = =	= = = =	= = =	= = =	REFERENC	ES =	= = = =	z = = =	= = = =	= =
1	-	27*	36								
5	-	25	28*								
3	~	29	37*								
4	-	42*	61	14							
5	-	40	43*								
6	-	54	5/*								
1	-	50	58*								
8	-	47	59*								
9	-	48	62*								
10	-	07	70×								
11	~	63	71*								
12	***	44	75*	102	198						
13	~	91	94*								
14	-	96	97∗								
15	~	63	96	98*							
16	-	19	103*								
17	-	17	109*								
18	-	111*									
19	-	26	113*								
20	~	41	115*								
601	-	19RD	117*								
602	-	20RD	118*								
603	-	21 WR	119*								
604	-	24RD	39R0	120*							
605	-	111WR	121*								
606	-	113WR	122*								
607	-	115WR	123*								
A	~	1401	20RD	21WK							
AWR	-	. 3()=	33AG								
В	~	1600									
BCD	-	1 [N	2=	28A6	32AG	35 A G	43AG	52AG	56 A G	60 A G	65 A G
		69AG	73AG	76AG	#1AG	85 A G	89AG	93AG	101AG	104AG	107AG
C 1	-	1600									
C S		1000	30								
CKHD	-	45	78								
CONT	•	1 l N	3=								
COUN	-	1500									
END	•	19RD	SORD								
ESEGPR	**	109									
FEND	-	1 1 N	4 =								
FIL14	-	53	57	วช	66	70	71				
FIL15	-	02	87	90	94	95	97	99	105		
FIL3	-	33									
HEAD	-	1 I N	5=	SYAG	. 88AG	42AG	43AG	75AG	76 A G		
HOL	-	1 I N	6=								
í	-	20KD	21 WR	54	67	91					
J	-	50	63	83							
TNL	-	1600									

INDE	Х										PAGE 7
		****	*****	*****	*****	*****	****	*****	****	***	
1.1	-	1600	47	19							
Ľ5	-	1600	48	86							
L G		15CD	40	•							
LIST		7=	68AG	69AG	103AG	104AG					
LNT		25	40	0744	IOSHU	10484					
MAT	-	1600	40								
MATW	-	19RD	22AG	37AG	113WR						
MEND	-	8=	2270	3173	11341						
MF	-	1600	29	44	45AG	77	78AG				
MODE	-	19RD	22AG	27AG	31AG	34AG	37AG	42AG	51 A G	55AG	59AG
11004		64AG	68AG	72AG	/5AG	80AG	84AG	88AG	92AG	100AG	103AG
		106AG	113WR		. 314	0-4-	- ,,	0071		10044	10574
мт	-	1600	46AG								
N 1	_	16CU									
NIX	-	1600	17=								
NS	-	1600									
N2X	•	1600	18=								
NBT	•	1600	* • · ·								
NC	-	1500	49	62							
ND	-	1500	49	62							
NE	-	1500	54	67	91						
NI	_	1500			-						
NK	-	1500	83								
NP	-	1500									
NS		1600	24RD	39RD							
NS1	-	1500									
NT	-	19KD	22AG	23	24RD	27AG	31 A G	34AG	37AG	38	39RD
		42AG	51AG	55 A G	59AG	64AG	68AG	72AG	75AG	BOAG	84AG
		BBAG	92AG	100AG	103AG	106AG	113WK				-,
NTA	•	49=	50	62=	63						
NTAB	-	1500									
RECS	•	1600									
RREC	-	27	31	34	42	51	55	59	64	68	72
		75	80	84	88	92	100	103	106		
SEARCH	-	22	37								
SEND		1 l N	9=	34AG	35AG	59AG	60AG	72AG	73AG	100AG	101AG
		1 06 A G	107AG								-
STOP	-	110	112	114	116						
TAB1	-	1 I N	10=	31 A G	32AG	55AG	56AG	80 A G	81 A G	84AG	85AG
		92AG	93AG								
TAB2	-	1 I N	11=	51 A G	52AG	64AG	65AG	88 A G	89 A G		
TEND	-	1 I N	12=								
TEST20	-	46									
TPID	**	1 I N	13=						_		
WREC	-	28	32	35	43	52	56	60	65	69	73
		(6	81	85	89	93	101	104	107		
X	-	1600									
Y	-	1600									
-+-+-+	+-+-	+=+=+		-+-+-+-	*+*+*+**		-+-+-+-+				

```
INDEX
                                                                                        PAGE
                                                                                               8
             *************
                 SUBROUTINE CKHD(FILE)
                                                                                        CHD
    1
                                                                                              1
                 COMMON/COUN/LG, NC, ND, NE, NI, NK, NP, NTAB, NS1
    2
                                                                                        CHD
                                                                                              2
                 CUMMON/RECS/MAT, MF, MT, C1, C2, L1, L2, N1, N2, NBT(100), JNT(100), X(2000), CHD
    3
                                                                                              3
                              Y(2000),B(2000);N1X,N2X,N5
                                                                                        CHD
                                                                                              4
    4
                 IF (FILE .NE. 14) GU TO 4
                                                                                        CHD
                                                                                              5
          C
                                                                                        CHD
                                                                                              6
          C----CHECK FILE 14 HEAD CARD.
                                                                                        CHD
                                                                                              7
          C
                 CHECK LI.
                                                                                        CHD
                                                                                              8
          C
                                                                                        CHD
                                                                                              o
    5
                 IF (L1.EQ.O .UR. L1.EQ.1) GO TO 1
                                                                                        CHD
                                                                                             10
                 WRITE (6,601)
    6
                                                                                        CHD
                                                                                             11
                L1 = 0
                                                                                        CHD
                                                                                             12
          C
                                                                                        CHD
                                                                                             13
          C
                 CHECK LTT.
                                                                                        CHD
                                                                                             14
          C
                                                                                        CHD
                                                                                             15
   8
              1 IF (L2.EQ.1 .UR. L2.EQ.2) GD TO 2
                                                                                        CHD
                                                                                             16
                WRITE (6,602)
                                                                                       CHD
                                                                                             17
   10
                L2 = 2
                                                                                       CHD
                                                                                             18
          C
                                                                                       CHD
                                                                                             19
          C
                CHECK ND.
                                                                                       CHD
                                                                                             20
          C
                                                                                       CHD
                                                                                             21
  11
              2 IF (N1 .GT. (MT=4)) WRITE (6,603)
                                                                                       CHD
                                                                                             22
          C
                                                                                       CHD
                                                                                             23
          C
                CHECK NO.
                                                                                       CHD
                                                                                             24
          C
                                                                                       CHD
                                                                                             25
                IF (N2.E0.0 .OR. N2.E0.1) GO TO 3
  12
                                                                                       CHD
                                                                                             26
  13
                WRITE (6,604)
                                                                                       CHD
                                                                                             27
  14
                N2 = 1
                                                                                       CHD
                                                                                             28
  15
              3 ND = N1
                                                                                       CHD
                                                                                             29
                NC = N2
  16
                                                                                       CHD
                                                                                             30
  17
                RETURN
                                                                                       CHD
                                                                                             31
              4 IF (FILE .NE. 15) GO TO 10
  18
                                                                                       CHD
                                                                                             32
          C
                                                                                       CHD
                                                                                            33
          C----CMECK FILE 15 HEAD CARD.
                                                                                       CHD
                                                                                             34
          Ċ
                CHECK LO.
                                                                                       CHD
                                                                                             35
                                                                                       CHD
                                                                                            36
                IF (L1 .EQ. 2) GO TO 7
  19
                                                                                       CHD
                                                                                             37
                IF (L1 .EQ. 1) GO TO 5
  20
                                                                                       CHD
                                                                                             38
  21
                WRITE (6,605)
                                                                                       CHD
                                                                                            39
  22
                L1 = 1
                                                                                       CHD
                                                                                            40
  23
              5 IF (L2 .NE. 0) WRITE (6,606)
                                                                                       CHD
                                                                                            41
          C
                                                                                       CHD
                                                                                            42
          C
                CHECK ND.
                                                                                       CHD
                                                                                            43
          C
                                                                                       CHD
                                                                                            44
  24
                IF (N1 .GT. (MT-4)) WRITE (6,603)
                                                                                       CHD
                                                                                            45
          С
                                                                                       CHD
                                                                                            46
          C
                CHECK NK.
                                                                                       CHD
                                                                                            47
          С
                                                                                       CHD
                                                                                            48
  25
                IF (N2 .GE. N1) GO TO 6
                                                                                       CHD
                                                                                            49
  26
                WRITF (6,607)
                                                                                       CHD
                                                                                            50
```

PAGE 9 INDEX SUBROUTINE CKHD(FILE) 51 27 N2 = N1CHD CHD 6 ND = N1 52 28 CHD NK = N253 29 RETURN CHD 54 30 CHD 55 C CHD 56 С CHECK LG. 57 CHD C 7 IF (L2.EQ.1 .OR. L2.EQ.2) GO TO 8 CHD 58 31 WRITE (6,608) 59 CHD 32 CHD 60 L2 = 3 33 C CHD 61 CHD С CHECK NS. 62 CHD 63 C 8 IF (N1 .LE. (MT-4)) GU TO 9 CHD 64 34 WRITE (6,609) CHD 65 35 NS1 = MT -4 CHD 66 36 CHD 67 9 IF (N2 .NE. 0) WRITE (6,610) 37 CHD 68 38 L6 = L2 CHD 39 RETURN 69 10 WRITE (6,611) CHD 70 40 41 RETURN CHD 71 601 FORMAT (15(1H*), 46H LI NOT IN DEFINED RANGE. LI SET EQUAL TO 0. CHD 72 42 1, 49(1H*)) CHD 73 602 FORMAT (15(1H*), 48H LTT NOT IN DEFINED RANGE. LTT SET EQUAL TO 2CHD 74 43 75 CHD 1. , 47(1H*)) 603 FORMAT (15(1H*), 84H ND LARGER THAN STATE LEVEL WILL ALLOW. WILL CHD 76 44 1CONTINUE PROCESSING WITH ND AS GIVEN. . 11(1H+)) 77 CHD 604 FORMAT (15(1H*), 46H NO NOT IN DEFINED HANGE. NO SET EQUAL TO 1. CHD 78 45 1, 49(1H*)) CHD 79 605 FORMAT (15(1H*), 46H LO NOT IN DEFINED RANGE. LO SET EQUAL TO 1. CHD 80 46 81 CHD 1, 49(1H*)) 606 FORMAT (15(1H*), 27H FOURTH FIELD SHOULD BE 0,, 68(1H*)) CHD 82 47 507 FURMAT (15(1H*), 42H ND GREATER THAN NK. NK SET EQUAL TO NO. . 64CHD 83 48 CHD 84 1(1H*)608 FORMAT (15(1H*), 73H LG NOT IN DEFINED RANGE. PROCESSING OF THIS SCHO 85 49 1ECTION WILL BE ATTAMPTED. , 22(1H*)) CHD 86 609 FORMAT (15(1H*), 70H HS LARGER THAN STATE LEVEL WILL ALLOW. NS SECHD 87 50 IT EQUAL TO STATE LEVEL. , 25(1H*)) CHD 88 510 FURMAT (15(14*), 26H SIXTH FIELD SHOULD BE 0. , 69(1H*)) CHD 89 51 611 FORMAT (15(1H+), 36H HEAD CARD NOT PROCESSED DUE TO MF. ,59(1H+)) 90 CHD 52 CHD 91-

53

END

SUBROUTINE CKHD(FILE)

1	SYMBOL		= = = =	= = =	= = =	= = =	REFERE	ENCES :	= = =		= = =	= =	= =
3 - 12 15* 4 - 4 16* 5 - 20 23* 6 - 25 28* 7 - 19 31* 8 - 31 34* 9 - 34 37* 10 - 18 40* 602 - 9HR 42* 602 - 9HR 43* 604 - 13HR 24HR 44* 604 - 13HR 45* 605 - 21HR 46* 606 - 23HR 40* 606 - 23HR 40* 606 - 23HR 40* 606 - 35HR 50* 610 - 35HR 50* 610 - 37HR 51* 611 - 40HR 52* B - 3CO C1 - 3CO CKHD - 1 CUUN - 2CO CKHD - 1 CUUN - 2CO FILE - 1AG 4 18 JNT 3CO L1 - 3CO 5 7= 19 20 22= L2 - 3CO 8 10= 23 31 33= 38 LG - 2CO 38= MAT 3CO MF - 3CO MF - 3CO MF - 3CO MF - 3CO N2 - 3CO 11 24 34 36 N1 - 3CO 12 14= 16 25 27= 29 37 N1 - 3CO N2 - 3CO N4 - 3CO 10 15= 28= N6 - 2CO N8 - 3CO N8 - 2CO N8 - 3CO N8 - 2CO	1	-	5	8*									
3 - 12 15* 4 - 4 16* 5 - 20 23* 6 - 25 28* 7 - 19 31* 8 - 31 34* 9 - 34 37* 10 - 18 40* 601 - 6MR 42* 602 - 9HR 43* 603 - 11HR 24HR 44* 604 - 13HR 45* 605 - 21HR 46* 606 - 23HR 47* 607 - 26HR 48* 608 - 32HR 49* 609 - 35HR 50* 610 - 37HR 51* 611 - 40MR 52* 8 - 3CO CL - 3CO CKHD - 1 CUUN - 2CO FILE - 1AG 4 18 JNT 3CO L1 - 3CO 5 7= 19 20 22= L2 - 3CO 8 10= 23 31 33= 36 LG - 2CO 38= MAT 3CO MF - 3CO MF - 3CO MF - 3CO N2 - 3CO N2 - 3CO N2 - 3CO N1 - 3CO N2 - 3CO N3 - 3CO N2 - 3CO N2 - 3CO N4 - 3CO N5 - 3CO N6 - 3CO N6 - 3CO N7 - 3CO N8 - 3CO N8 - 2CO N8 - 3CO N8 - 2CO N8 - 2CO N8 - 2CO N8 - 3CO	2	-	8	11*									
9 - 34 37* 10 - 18 40* 601 - 6WR 42* 602 - 9WR 43* 603 - 11WR 24WR 49* 604 - 13WR 45* 605 - 21WR 46* 606 - 23WR 47* 607 - 26WR 48* 608 - 32WR 49* 609 - 35WR 50* 610 - 37WR 51* 611 - 40WR 52* 8 - 3CD C1 - 3CD C2 - 3CD C2 - 3CD C2 - 3CD C2 - 3CD C4 - 11 - 3CD C5 - 7= 19 20 22= L1 - 3CD L1 - 3CD 5 7= 19 20 22= L2 - 3CD 8 10= 23 31 33= 38 LG - 2CD 38= MAT - 3CD MF - 3CD N1 - 3CD N2 - 3CD N2 - 3CD N3 - 3CD N6 - 2CD N7 - 3CD N8 - 2CD N8 - 3CD N8	3	-	12	15*									
9 - 34 37* 10 - 18 40* 601 - 6WR 42* 602 - 9WR 43* 603 - 11WR 24WR 49* 604 - 13WR 45* 605 - 21WR 46* 606 - 23WR 47* 607 - 26WR 48* 608 - 32WR 49* 609 - 35WR 50* 610 - 37WR 51* 611 - 40WR 52* 8 - 3CD C1 - 3CD C2 - 3CD C2 - 3CD C2 - 3CD C2 - 3CD C4 - 11 - 3CD C5 - 7= 19 20 22= L1 - 3CD L1 - 3CD 5 7= 19 20 22= L2 - 3CD 8 10= 23 31 33= 38 LG - 2CD 38= MAT - 3CD MF - 3CD N1 - 3CD N2 - 3CD N2 - 3CD N3 - 3CD N6 - 2CD N7 - 3CD N8 - 2CD N8 - 3CD N8	4	•.	4	18*									
9 - 34 37* 10 - 18 40* 601 - 6WR 42* 602 - 9WR 43* 603 - 11WR 24WR 49* 604 - 13WR 45* 605 - 21WR 46* 606 - 23WR 47* 607 - 26WR 48* 608 - 32WR 49* 609 - 35WR 50* 610 - 37WR 51* 611 - 40WR 52* 8 - 3CD C1 - 3CD C2 - 3CD C2 - 3CD C2 - 3CD C2 - 3CD C4 - 11 - 3CD C5 - 7= 19 20 22= L1 - 3CD L1 - 3CD 5 7= 19 20 22= L2 - 3CD 8 10= 23 31 33= 38 LG - 2CD 38= MAT - 3CD MF - 3CD N1 - 3CD N2 - 3CD N2 - 3CD N3 - 3CD N6 - 2CD N7 - 3CD N8 - 2CD N8 - 3CD N8	5	-		23*									
9 - 34 37* 10 - 18 40* 601 - 6WR 42* 602 - 9WR 43* 603 - 11WR 24WR 49* 604 - 13WR 45* 605 - 21WR 46* 606 - 23WR 47* 607 - 26WR 48* 608 - 32WR 49* 609 - 35WR 50* 610 - 37WR 51* 611 - 40WR 52* 8 - 3CD C1 - 3CD C2 - 3CD C2 - 3CD C2 - 3CD C2 - 3CD C4 - 11 - 3CD C5 - 7= 19 20 22= L1 - 3CD L1 - 3CD 5 7= 19 20 22= L2 - 3CD 8 10= 23 31 33= 38 LG - 2CD 38= MAT - 3CD MF - 3CD N1 - 3CD N2 - 3CD N2 - 3CD N3 - 3CD N6 - 2CD N7 - 3CD N8 - 2CD N8 - 3CD N8	6	-											
9 - 34 37* 10 - 18 40* 601 - 6WR 42* 602 - 9WR 43* 603 - 11WR 24WR 49* 604 - 13WR 45* 605 - 21WR 46* 606 - 23WR 47* 607 - 26WR 48* 608 - 32WR 49* 609 - 35WR 50* 610 - 37WR 51* 611 - 40WR 52* 8 - 3CD C1 - 3CD C2 - 3CD C2 - 3CD C2 - 3CD C2 - 3CD C4 - 11 - 3CD C5 - 7= 19 20 22= L1 - 3CD L1 - 3CD 5 7= 19 20 22= L2 - 3CD 8 10= 23 31 33= 38 LG - 2CD 38= MAT - 3CD MF - 3CD N1 - 3CD N2 - 3CD N2 - 3CD N3 - 3CD N6 - 2CD N7 - 3CD N8 - 2CD N8 - 3CD N8	7	-	19	31*									
10 - 18	8	-		34*									
601 - 6HR 42* 602 - 9HR 43* 603 - 11MR 24HR 44* 604 - 13MR 45* 605 - 21MR 46* 606 - 23MR 47* 607 - 26HR 48* 608 - 32HR 49* 609 - 35HR 50* 610 - 37HR 51* 611 - 40MR 52* B - 3C0 C1 - 3C0 C2 - 3C0 C1 - 3C0 C2 - 3C0 C1 - 3C0 C1 - 3C0 C2 - 3C0 C1 - 3C0 C1 - 3C0 C2 - 3C0 C1 - 3C0 C1 - 3C0 C2 - 3C0 C1 - 3C0 C1 - 3C0 C2 - 3C0 C2 - 3C0 C3 - 3C0 C4 - 3C0 C5 - 7= 19 20 22= L2 - 3C0 8 10= 23 31 33= 38 LG - 2C0 38= MAT - 3C0 MF - 3C0 MF - 3C0 MF - 3C0 MF - 3C0 MT - 3C0 11 24 34 36 N11 - 3C0 N1X - 3C0 N2 - 3C0 N2 - 3C0 N5 - 3C0 N6 - 2C0 16= N0 - 2C0 16= N0 - 2C0 15= 28= NF - 2C0 NK - 2C0 29= NF - 2C0 NK - 2C0 36= NS - 3C0 NS -	9	•		37*									
602 - 9WR 43* 603 - 11WR 24WR 44* 604 - 13WR 45* 605 - 21WR 46* 606 - 23WR 47* 607 - 26WR 48* 608 - 32WR 49* 609 - 35WR 50* 610 - 37WR 51* 611 - 40WR 52* 8 - 3CO C1 - 3CO C2 - 3CO CKHO - 1 COUN - 2CO FILE - 1AG 4 18 JNT - 3CO L1 - 3CO L1 - 3CO C5 7= 19 20 22= L2 - 3CO 8 10= 23 31 33= 38 LG - 2CO 38= MAT - 3CO MF - 3CO N1 - 3CO N1 - 3CO N2 - 3CO N3 - 3CO N4 - 2CO N5 - 3CO N6 - 2CO N6 - 2CO N6 - 2CO N7 - 2CO N8 - 3CO N8 - 3C	10	-	18	40*									
603 - 11WR 24WR 44* 604 - 13WR 45* 605 - 21WR 46* 606 - 23WR 47* 607 - 26WR 48* 609 - 35WR 50* 610 - 37WR 51* 611 - 40WR 52* 8 - 3CO C1 - 3CO C2 - 3CO CKHD - 1 COUN - 2CO FILE - 1AG 4 18 JNT - 3CO L1 - 3CO 5 7= 19 20 22= L2 - 3CO 8 10= 23 31 33= 38 LG - 2CO 8 10= 23 31 33= 38 LG - 2CO 8 38= MAT - 3CO MF - 3CO MF - 3CO MF - 3CO N1 - 3CO 11 24 34 36 N1 - 3CO 11 15 24 25 27 28 34 N1X - 3CO N2 - 3CO N5 - 2CO 16= ND - 2CO 15= 28= NE - 2CO NK - 2CO 29= NP - 2CO NS - 3CO NS	601	-	6WR										
604 - 134R 45* 605 - 214R 46* 606 - 234R 47* 607 - 264R 48* 608 - 324R 49* 609 - 354R 50* 610 - 374R 51* 611 - 404R 52* B - 3C0 C1 - 3C0 C2 - 3C0 CKHD - 1 COUN - 2C0 FILE - 146 4 18 JNT - 3C0 L1 - 3C0 5 7= 19 20 22= L2 - 3C0 8 10= 23 31 33= 38 LG - 2C0 38= MAT - 3C0 MF - 3C0 MF - 3C0 MF - 3C0 MT - 3C0 11 24 34 36 N1 - 3C0 11 15 24 25 27 28 34 N1X - 3C0 N2 - 3C0 12 14= 16 25 27= 29 37 N2X - 3C0 NBT - 3C0 NC - 2C0 16= ND - 2C0 15= 28= NE - 2C0 NK - 2C0 NK - 2C0 NS - 3C0 NS - 3													
605 - 21 MR 46+ 606 - 23 MR 47+ 607 - 26 MR 48+ 608 - 32 MR 49+ 609 - 35 MR 50+ 610 - 37 MR 51+ 611 - 40 MR 52+ B - 3C0 C1 - 3C0 C2 - 3C0 CKHD - 1 COUN - 2C0 FILE - 1AG 4 18 JNT - 3C0 L1 - 3C0 5 7= 19 20 22= L2 - 3C0 8 10= 23 31 33= 38 LG - 2C0 38= MAT - 3C0 MF - 3C0 MT - 3C0 MT - 3C0 MT - 3C0 N1 - 3C0 N2 - 3C0 N3 - 3C0 N6 - 2C0 N6 - 2C0 N7 - 2C0 N8 - 3C0 N8 -				24 WR	44*								
606 - 23 WR 47* 607 - 26 WR 48* 608 - 32 WR 49* 609 - 35 WR 50* 610 - 37 WR 51* 611 - 40 WR 52* B - 3C0 C1 - 3C0 C2 - 3C0 CC - 3C0 CC - 3C0 CT - 3C0 C1 - 3C0 C2 - 3C0 C4 - 3C0 C5 - 7= 19 20 22= L2 - 3C0 8 10= 23 31 33= 38 LG - 2C0 38= MAT - 3C0 MF - 3C0 MF - 3C0 MF - 3C0 MF - 3C0 MT - 3													
607 - 26WR 48* 608 - 32WR 49* 609 - 35WR 50* 610 - 37WR 51* 611 - 40WR 52* B - 3C0 C1 - 3C0 C2 - 3C0 C2 - 3C0 CKHD - 1 COUN - 2C0 FILE - 1AG 4 18 JNT - 3C0 L1 - 3C0 5 7= 19 20 22= L2 - 3C0 8 10= 23 31 33= 38 LG - 2C0 38= MAT - 3C0 MF		-	21WR										
608 - J2MR 49+ 609 - J5MR 50+ 610 - J7MR 51+ 611 - 40MR 52+ B - 3C0 C1 - 3C0 C2 - 3C0 CKHD - 1 COUN - 2C0 FILE - 1AG 4 18 JNT - 3C0 L1 - 3C0 L2 - 3C0 8 10= 23 31 33= 38 LG - 2C0 38= MAT - 3C0 MF - 3C0 MF - 3C0 MT - 3C0 MT - 3C0 11 24 34 36 N1 - 3C0 MT - 3C0 11 15 24 25 27 28 34 N1X - 3C0 N2 - 3C0 12 14= 16 25 27= 29 37 N2X - 3C0 NBT - 3C0 NC - 2C0 16= ND - 2C0 15= 28= NE - 2C0 NS - 3C0 N		•											
609 - J5WR 50+ 610 - J7WR 51+ 611 - 40WR 52+ B - 3C0 C1 - 3C0 C2 - 3C0 CKHD - 1 COUN - 2C0 FILE - 1AG 4 18 JNT - 3C0 5 7= 19 20 22= L2 - 3C0 8 10= 23 31 33= 38 LG - 2C0 38= MAT - 3C0 MF - 3C0 MT - 3C0 11 24 34 36 N1 - 3C0 11 15 24 25 27 28 34 N1X - 3C0 N2 - 3C0 12 14= 16 25 27= 29 37 N2X - 3C0 NBT - 3C0 NBT - 3C0 NBT - 3C0 NC - 2C0 16= ND - 2C0 15= 28= NE - 2C0 NI - 2C0 NI - 2C0 NI - 2C0 NS - 3C0		•	26WR										
610 - 37MR 51+ 611 - 40MR 52* B - 3C0 C1 - 3C0 C2 - 3C0 CKHD - 1 CCUN - 2C0 FILE - 1AG	608	-	32WR	49*									
610 - 37MR 51+ 611 - 40MR 52* B - 3C0 C1 - 3C0 C2 - 3C0 CKHD - 1 CCUN - 2C0 FILE - 1AG	609	-	35WR	50*									
611 - 40 WR 52 * 8	610	-	37WR	51*									
B - 3C0 C1 - 3C0 C2 - 3C0 C2 - 3C0 CKHD - 1 COUN - 2C0 FILE - 1AG		•	40WR										
C1 - 3C0 C2 - 3C0 CKHD - 1 COUN - 2C0 FILE - 1AG 4 18 JNT - 3C0 L1 - 3C0 5 7= 19 20 22= L2 - 3C0 8 10= 23 31 33= 38 LG - 2C0 38= MAT - 3C0 MF - 3C0 MT - 3C0 11 24 34 36 N1 - 3C0 11 15 24 25 27 28 34 N1X - 3C0 N2 - 3C0 12 14= 16 25 27= 29 37 N2X - 3C0 NBT - 3C0 NBT - 3C0 NBT - 3C0 NC - 2C0 16= ND - 2C0 15= 28= NE - 2C0 NK - 2C0 29= NP - 2C0 NS - 3C0 NS - 3C0		-		-									
C2 - 3C0 CKHD - 1 COUN - 2C0 FILE - 1AG	C 1	-											
CKHD - 1 COUN - 2CO FILE - 1AG 4 18 JNT - 3CO L1 - 3CO 5 7= 19 20 22= L2 - 3CO 8 10= 23 31 33= 38 LG - 2CO 38= MAT - 3CO MF - 3CO MF - 3CO MT - 3CO 11 24 34 36 N1 - 3CO 11 15 24 25 27 28 34 N1X - 3CO N2 - 3CO 12 14= 16 25 27= 29 37 N2X - 3CO NBT - 3CO NBT - 3CO NC - 2CO 16= ND - 2CO 15= 28= NE - 2CO NK - 2CO 29= NF - 2CO NK - 2CO 29= NF - 2CO NS1 - 3CO NS1 - 2CO 36=		-											
COUN - 2CO FILE - 1AG	CKHD	•	1										
JNT - 3C0 L1 - 3C0 5 7= 19 20 22= L2 - 3C0 8 10= 23 31 33= 38 LG - 2C0 38= MAT - 3C0 MF - 3C0 MT - 3C0 11 24 34 36 N1 - 3C0 11 15 24 25 27 28 34 N1X - 3C0 N2 - 3C0 12 14= 16 25 27= 29 37 N2X - 3C0 NBT - 3C0 NC - 2C0 16= ND - 2C0 15= 28= NE - 2C0 NI - 2C0 NI - 2C0 NI - 2C0 NI - 2C0 NS - 3C0 NS - 3	COUN	-											
L1 - 3C0 5 7= 19 20 22= L2 - 3C0 8 10= 23 31 33= 38 LG - 2C0 38= MAT - 3C0 MF - 3C0 MT - 3C0 11 24 34 36 N1 - 3C0 11 15 24 25 27 28 34 N1X - 3C0 N2 - 3C0 12 14= 16 25 27= 29 37 N2X - 3C0 NBT - 3C0 NC - 2C0 16= ND - 2C0 15= 28= NE - 2C0 NI - 2C0 NI - 2C0 NI - 2C0 NS - 3C0 NS1 - 2C0 36=	FILE	-	1 A G	4	18								
L2 - 3CO 8 10= 23 31 33= 38 LG - 2CO 38= MAT - 3CO MF - 3CO MT - 3CO 11 24 34 36 N1 - 3CO 11 15 24 25 27 28 34 N1X - 3CO N2 - 3CO 12 14= 16 25 27= 29 37 N2X - 3CO NBT - 3CO NC - 2CO 16= ND - 2CO 15= 28= NE - 2CO NI - 2CO NI - 2CO NI - 2CO NI - 2CO NS - 3CO NS - 3CO NS1 - 2CO 36=		-											
LG - 2CO 38= MAT - 3CO MF - 3CO MT - 3CO 11 24 34 36 N1 - 3CO 11 15 24 25 27 28 34 N1X - 3CO N2 - 3CO 12 14= 16 25 27= 29 37 N2X - 3CO NBT - 3CO NC - 2CO 16= ND - 2CO 15= 28= NE - 2CO NI - 3CO NI - 2CO		-	3 C O	5		19	20						
LG - 200 38= MAT - 300 MF - 300 MT - 300 11 24 34 36 N1 - 300 11 15 24 25 27 28 34 N1X - 300 N2 - 300 12 14= 16 25 27= 29 37 N2X - 300 NBT - 300 NC - 200 16= ND - 200 15= 28= NE - 200 NI - 200 NK - 200 29= NP - 200 NS - 300 NS1 - 200 36=		-			10=	23	31	33=	38				
MF - 3C0 MT - 3C0 11 24 34 36 N1 - 3C0 11 15 24 25 27 28 34 N1X - 3C0 N2 - 3C0 12 14= 16 25 27= 29 37 N2X - 3C0 NBT - 3C0 NC - 2C0 16= ND - 2C0 15= 28= NE - 2C0 NI - 2C0 NI - 2C0 29= NP - 2C0 NS - 3C0 NS1 - 2C0 36=	LG		200	38=									
MT - 3C0 11 24 34 36 N1 - 3C0 11 15 24 25 27 28 34 N1X - 3C0 N2 - 3C0 12 14= 16 25 27= 29 37 N2X - 3C0 NBT - 3C0 NC - 2C0 16= ND - 2C0 15= 28= NE - 2C0 NI - 2C0 NK - 2C0 29= NP - 2C0 NS - 3C0 NS - 3C0 NS1 - 2C0 36=		-											
N1 - 3C0 11 15 24 25 27 28 34 N1X - 3C0 N2 - 3C0 12 14= 16 25 27= 29 37 N2X - 3C0 NBT - 3C0 NC - 2C0 16= ND - 2C0 15= 28= NE - 2C0 NI - 2C0 NK - 2C0 29= NP - 2C0 NS - 3C0 NS1 - 2C0 36=	MF	•											
N1 - 3C0 11 15 24 25 27 28 34 N1X - 3C0 N2 - 3C0 12 14= 16 25 27= 29 37 N2X - 3C0 NBT - 3C0 NC - 2C0 16= ND - 2C0 15= 28= NE - 2C0 NI - 2C0 NK - 2C0 29= NP - 2C0 NS - 3C0 NS1 - 2C0 36=		-		11	24		36						
N2 - 300 12 14= 16 25 27= 29 37 N2X - 300 NBT - 300 NC - 200 16= ND - 200 15= 28= NE - 200 NI - 200 NK - 200 29= NP - 200 NS - 300 NS1 - 200 36=				11	15	24	25	27	28	34			
N2X - 3CD NBT - 3CO NC - 2CO 16= ND - 2CO 15= 28= NE - 2CO NI - 2CO NK - 2CO 29= NP - 2CO NS - 3CO NS1 - 2CO 36=													
NBT - 3C0 NC - 2CO 16= ND - 2CO 15= 28= NE - 2CO NI - 2CO NK - 2CO 29= NP - 2CO NS - 3CO NS1 - 2CO 36=	N2		3C0	12	1 4 =	16	25	27=	29	37			
NC - 200 16= ND - 200 15= 28= NE - 200 NI - 200 NK - 200 29= NP - 200 NS - 300 NS1 - 200 36=		-											
ND - 200 15= 28= NE - 200 NI - 200 NK - 200 29= NP - 200 NS - 300 NS1 - 200 36=			300										
NE - 200 NI - 200 NK - 200 29= NP - 200 NS - 300 NS1 - 200 36=	NC		200										
NI - 200 NK - 200 29= NP - 200 NS - 300 NS1 - 200 36=			sco	15=	28=								
NK - 200 29= NP - 200 NS - 300 NS1 - 200 36=		-											
NP - 200 NS - 300 NS1 - 200 36=			500										
NS - 3CO NS1 - 2CO 36=	NK		2CO .	29=									
NS1 - 200 36=	NP		200										
NS1 = 200 36=	NS	-											
	NS1	-	2 C 0	36=									
NTAB - 2CO	NTAB	-	500										

INDEX PAGE 11

SUBROUTINE CKHO(FILE)

RECS = 300 RETURN = 17 30 39 41 X = 300 Y = 300

SUBROUTINE FIL3(AWR)

```
SUBROUTINE FIL3(AWR)
                                                                                               1
              COMMON/RECS/MAT, MF, MT, C1, C2, L1, L2, N1, N2, NBT(100), JNT(100), X(2000), F 3
                                                                                              2
 2
                            Y(2000), B(2000) FN1X, N2X, NS
                                                                                        F
                                                                                               3
              CUMMON/SAVE/ETH(300),@(300),ETAB(2000),YTAB(2000),YKTAB(2000),
                                                                                        F
 3
                                                                                          3
                                                                                              Δ
                            YCAL(2000), YTIL(2000), EK(2000), YK(2000), ES(40)
                                                                                        F
                                                                                              5
                                                                                          3
                                                                                        F
        C
                                                                                          3
                                                                                              6
        C---TEST Q.
                                                                                        F
                                                                                          3
                                                                                              7
        C
                                                                                        F
                                                                                          3
                                                                                              8
              IF (MT.LE.4 .OR. (MT.GE.15 .AND. MT.LE.50) .OR. MT.GE.81) GO TO 1
                                                                                       F
 4
                                                                                              9
              IF (C2 .GE. 0.0) WRITE (6,601)
 5
                                                                                             10
              IF (ABS(C2).LT.1.0*10**4 .OR. ABS(C2).GT.2.0*10**7) WRITE (6,602)
 6
                                                                                          3
                                                                                             11
 7
            1 IF (MT.NE.15 .AND. MT.NE.110) GO TO 2
                                                                                          3
                                                                                             12
                                                                                        F
              IF (C2 .E4. 0.0) GO TO 2
 8
                                                                                          3
                                                                                             13
 9
                                                                                        F
              WRITE (6,603)
                                                                                          3
                                                                                             14
10
                                                                                        F
              C2 = 0.0
                                                                                          3
                                                                                             15
            2 IF (MT .NE. 102) GO TO 3
                                                                                        F
                                                                                          3
11
                                                                                             16
12
              IF (C2 .LT. 0.0) WRITE (6,604)
                                                                                        F
                                                                                          3
                                                                                             17
              IF (C2.NE.O .AND. (C2.LT.1.7+10++6 .OR. C2.GT.1.2+10++7)) WRITE (6F
13
             1,605)
                                                                                        F
                                                                                          3
                                                                                             19
                                                                                        F
       C
                                                                                             20
                                                                                          3
                                                                                       F.
       C----CALCULATE AND TEST THRESHOLD.
                                                                                          3
                                                                                             21
       С
                                                                                          3
                                                                                             22
            3 ETHED = (AWR+1)*ABS(CE)/AWR
                                                                                        F
                                                                                             23
14
                                                                                          3
                                                                                        F
15
              IF (C2 .GT. 0.0) ETHEU = 0.0
                                                                                          3
                                                                                             24
              IF (ETHEO.GT.X(1) .AND. C2.LT.O.O) WRITE (6,606) ETHEO
                                                                                        F
16
                                                                                          3
                                                                                             25
       C
                                                                                        F
                                                                                             26
                                                                                          3
       C----STORE Q AND THRESHOLD.
                                                                                       F
                                                                                             27
                                                                                          3
                                                                                       F
       C
                                                                                          3
                                                                                             28
                                                                                       F
17
              Q(MT)=C2
                                                                                          3
                                                                                             29
                                                                                        F
18
              ETH(MT) = X(1)
                                                                                          3
                                                                                             30
                                                                                       F
                                                                                             31
19
              IF (ETHED .GT. X(1)) ETH(MT) = ETHED
                                                                                          3
                                                                                       F
       C
                                                                                             32
                                                                                          3
                                                                                       F
       C----CALCULATE 2200 M/SEC CROSS SECTION, MT = 102.
                                                                                          3
                                                                                             33
                                                                                       F
       C
                                                                                          3
                                                                                             34
20
              IF (MT .NE. 102) GO TO 8
                                                                                       F
                                                                                          3
                                                                                             35
                                                                                       F
21
              K = 0
                                                                                          3
                                                                                             36
22
                                                                                       F
              IF (X(1) .GT. 0.0253) GD TO 9
                                                                                          3
                                                                                             37
                                                                                       F
23
              00 \ 4 \ I = 1 \cdot N2
                                                                                          3
                                                                                             38
              K = K + 1
                                                                                       F
24
                                                                                          3
                                                                                             39
              IF (X(I) .EQ. 0.0253) GO TO 5
                                                                                       F
                                                                                         3
25
                                                                                             40
            4 IF (X(1).LT.0.0253 .AND. X(I+1).GT.0.0253) GO TO 6
                                                                                       F
26
                                                                                          3
                                                                                             41
                                                                                             42
27
            5 WRITE (6,607) Y(K)
                                                                                          3
                                                                                       F
                                                                                             43
28
              G0 T0 8
                                                                                         3
                                                                                       F
29
            6 Du 7 I = 1, N1
                                                                                         3
                                                                                             44
                                                                                       F
30
            7 IF (K \cdot LE \cdot NBT(I)) INT = JNT(I)
                                                                                             45
                                                                                          3
31
              ENG = 0.0253
                                                                                       F
                                                                                          3
                                                                                             46
              CALL TERP1(X(K),Y(K),X(K+1),Y(K+1),ENG,SIGMA,INT)
32
                                                                                             47
                                                                                          3
              WRITE (6,607) SIGMA
33
                                                                                             48
                                                                                          3
                                                                                       F
34
            8 RETURN
                                                                                             49
                                                                                          3
35
                                                                                       F
                                                                                             50
            9 WRITE (6,608)
                                                                                         3
```

1 N E	D	Ł	X		PA	GE	13
				SUBMOUTINE FIL3(AWR)			
3	6			RETURN	F	3	51
37	7			601 FURMAT (15(1H*),28H Q SHOULD BE LESS THAN 0.0, ,67(1H*))	F	3	52
3 (8			602 FORMAT(15(1H+),46H & SHOULD BE IN THE RANGE 1.0E+04 TO 2.0E+07. ,4	4 F	3	53
				19(1H*))	F.	3	54
39	9			603 FORMAT (15(1H*), 76H @ SHOULD BE EQUAL TO 0.0. @ SET EQUAL TO 0.0	F	3	55
				1FOR REMAINDER OF PROCESSING. ,19(1H*))	F.	3	56
4 (0			604 FURMAT (15(1H*),43H Q SHOULD BE GREATER THAN OR EQUAL TO 0.0.,52	(F	3	57
				11H*))	F	3	58
4 :	1			605 FURNAT (15(1H+),74H WHEN Q IS NOT EQUAL TO 0.0, Q SHOULD BE IN THE	EF	3	59
				1 RANGE 1./E+06 TU 1.2E+07. ,21(1H+))	F	3	60
4:	2			606 FURMAT (15(1H*),65H EFFECTIVE THRESHOLD VALUE BELOW THEORETICAL AL	LF	3	61
	_			1LUMPD BY Q VALUE. >30(1H+)/15(1H+)>15H THEORETICAL = >1PE12.5>38X		-	62
				230(1H*))	F	_	63
<i>h</i> •	_					_	
4 ;	_			607 FURMAT (81(1H*),15H SIGMA(2200) = ,1PE12,5,2H B)	F	-	64
4 4	4			608 FORMAT $(81(11+),29H SIGMA(2200) = DATA NOT GIVEN)$	F :	3	65
4	5			END	F.	3	66=

INDEX PAGE 14

SYMBOL		2 2 2 2	= = = =	= = = =	= = z	REFEREN	NCES :	= = = =			= =
1	-	4	7*								
2 3 4 5 6 7	•	7	8	11*							
3	-	11	14*								
4	-	23	26±								
5	-	25	27±								
6	-	26	29*								
7	-	29	30*								
8	-	20	28	34*							
9	-	22	35*								
601	-	5WR	37*								
602	-	6WR	38*								
603	-	9₩R	39*								
604	•	12WR	40*								
605	-	13WR	41*								
606	•	16WR	42*								
607	-	27WR	33WR	43*							
608	-	35WR	44*								
ABS		6	14								
AWR	•	1 A G	14								
В	-	200									
C 1	•	200									
C 2	-	200	5	6	8	10=	12	13	14	15	16
		17				-			. .		
ΕK	•	300									
ENG	•	31=	32AG								
ES .	-	3CO									
ETAB	•	300									
ETH	•	300	18=	19=							
ETHEO	-	14=	15≃	16	19						
FIL3	•	1									
I	~	23	25	26	29	30					
INT	~	30=	32AG								
JNT	-	20 0	30								
K	-	21=	24=	27WR	30	32AG					
L1	•	200									
L2	-	200									
MAT	-	200									
MF	-	200									
MT	-	2 c 0	4	7	11	17	18	19	20		
N1	-	5 C0	29								
N1X	-	200									
N2	-	2C0	23								
N2X	-	200									
NBT	-	200	30								
NS	-	200	_								
0	-	300	17=								
RECS	-	500									
RETURN	-	34	36								

1 N D E	N D E X SUBROUTINE FIL3(AWR)										
				3	ווטטאפטין.	INE FIES	AWRJ				
SAVE	-	300									
SIGMA	-	32AG	33WR								
TERP1	-	32									
X	-	200	16	18	19	22	25	26	32AG		
Y	-	2CU	27WR	32AG	_						
YCAL	-	3 C O	-								
YK	-	300									
YKTAB	-	300									
YTAB	-	300									
YTIL	•	300									

INDEX	SUBROUTINE FIL14(N)	PAGE	16
	Spindoline Lietarn		
1	SUBROUTINE FIL14(N)	F14	1
2	COMMON/COUN/LG, NC, ND, NE, NI, NK, NP, NTAB, NS1	F14	2
3	COMMON/RECS/MAT, MF, MT, C1, C2, L1, L2, N1, N2, NBT(100), JNT(100), X(2000		3
	1 Y(2000),B(2000),N1X,N2X,NS	F14	4
4	COMMON/SAVE/ETH(300), Q(300), ETAB(2000), YTAB(2000), YKTAB(2000),	F14	5
-	1 YCAL(2000),YTIL(2000),EK(2000),YK(2000),ES(40) CDMMON/SAV14/EG,EN,ESI,IL,IN	F14 F14	6
5		F14	7
6	GO TO (1,6,9,1,10,9), N	F14	8 9
	CTEST TAR2 RECORD.	F14	10
	C 1231 TANS NEGOVO:	F14	11
7	1 NE = N2	F14	12
8	CALL ESEGPR(1)	F14	13
ğ	IF ((MT.GE.5 .AND. MT.LE.14) .OR. (MT.GE.51 .AND. MT.LE.80)) GD		14
	1 2	F14	15
	C .	F14	16
	C- MT IN RANGE 1-4, 15-50, 81-UP	F14	17
	C TEST ES AND EGI.	F14	18
	c	F14.	
10	IF (C2 .LT. 0.0) WRITE (6,601)	_	20
11	IF (C1 .LT. 0.0) WRITE (6,602)		21
12	IF (C1.NE.0.0 .AND. C2.GT.C1) WRITE (6,603)		22
	C TEST FOR CONTINUOUS SPECTRUM.		23 24
	C TEST FOR CONTINUOUS SPECTRUM.		25
13	Eu = 1.0		26
14	IF (MT ,F0. 110) GU TO 5		27
15	IF (C1.NE.0.0 .OR. C2.NE.0.0) GD TO 5		28
16	IL = IL + 1		29
17	IF (IL.EQ.1 .AND. NC.NE.1) WRITE (6,604)		30
18	IF (IL .GT. 1) WRITE (6,605)	F14	31
19	GD TO 5	F14	32
	C		33
	C MT IN RANGE 5-14, 51-80	-	34
	C TEST ES AND EGI.		35
.	C		36
20	2 IF (C2 .GE. 0.0) GU TO 3	F14	37
21 22	WRITE (6,601) IF (C1 .LT. 0.0) WRITE (6,602)		38 39
23	3 IF (C1 .LT. C2) WRITE (6,603)		40
24	IF (C1 .NE. ABS(Q(MT))) WRITE (6,606)		41
	C		42
	C TEST ORDER OF ES AND EGI.	F14	
	C	F14	44
25	IN = IN + 1	F14	45
26	IF (IN .GT. 1) GU TO 4		46
27	EST = C1	F14	47
28	£6 = C2		48
29 30	GU TO 5 4 IF (C1 .NE. ESI) WRITE (6,607)	F14 F14	49 50
30	A TO COT MACH COTA MUTIC COROCIA	r 14	J ()

```
51
      IF (C2 .GE. EG) WRITE (6,608)
                                                                           F14
                                                                                52
                                                                           F14
      EG = C2
                                                                           F14
                                                                                 53
C
                                                                           F14
      CHECK INTERPOLATION SCHEME
                                                                                 54
C
                                                                           F14
                                                                                 55
C
    5 IF (N2 .LE. N1) WRITE (6,609)
                                                                           F14
                                                                                 56
                                                                           F14
                                                                                 57
      IF (N1.NE.1 .OR. JNT(1).NE.2) WRITE (6,610)
                                                                           F14
                                                                                 58
      RETURN
                                                                           F14
                                                                                 59
C
                                                                           F14
                                                                                 60
C----TEST TAB1 RECORD.
                                                                           F14
C
      TABULATED FORM
                                                                                 61
                                                                           F14
                                                                                 62
C
    6 IF (N1.NE.1 .DR. JNT(1).NE.2) WRITE (6.611)
                                                                           F14
                                                                                 63
      IF (ETH(MT) .GT. C2) WRITE (6,612) ETH(MT)
                                                                            F14
                                                                                 64
      IF (C2 .LE. EN) WRITE (6,613)
                                                                            F14
                                                                                 65
                                                                           F14
                                                                                 66
      EN = C2
                                                                           F14
                                                                                 67
      08 7 I = 1, N2
    7 IF (Y(I).LT.0.499 .OR. Y(I).GT.0.501) GO TO 8
                                                                           F14
                                                                                 68
                                                                           F14
      IF (N2 .NE. 2) WRITE (6,614)
                                                                                 69
                                                                           F14
                                                                                 70
    8 RETURN
                                                                            F14
                                                                                 71
C
                                                                           F14
                                                                                 72
C----RE-INITIALIZE.
                                                                           F14
                                                                                 73
C
    9 IF (NC.EQ.1 .AND. IL.EQ.0) WRITE (6,615)
                                                                           F14
                                                                                 74
                                                                           F14
                                                                                 75
      IF (EG.EQ.0.0 .AND. IL.EQ.0) WRITE (6,616)
      IF (((MT.GE.5 .AND. MT.LE.14) .OR. (MT.GE.51 .AND. MT.LE.80)) .ANDF14
                                                                                 76
     1. NC.EQ.1) WRITE (6,617)
                                                                            F14
                                                                                 77
                                                                           F14
                                                                                 78
      EG = 0.0
                                                                            F14
                                                                                 79
      EN = 0.0
                                                                            F14
                                                                                 80
      ESI = 0.0
                                                                           F14
                                                                                 81
      IL = 0
                                                                            F14
                                                                                 82
      IM = 0
      RETURN
                                                                            F14
                                                                                 83
                                                                            F14
                                                                                 AΑ
C
                                                                            F14
                                                                                 85
C----TEST TAB1 RECORD.
C
      LEGENDRE POLYNOMIAL FORM
                                                                            F14
                                                                                 86
                                                                            F14
                                                                                 87
C
                                                                            F14
                                                                                 88
   10 IP (ETH(MT) .GT. C2) WRITE (6,612) ETH(MT)
                                                                            F14
                                                                                 89
      IF (C2 .LE. EN) WRITE (6,613)
      EN = C2
                                                                            F14
                                                                                 90
      RETURN
                                                                            F14
                                                                                 91
  601 FORMAT (15(1H*), 45H EGI SHOULD BE GREATER THAN OR EQUAL TO 0.0. ,5F14
                                                                                 92
                                                                            F14
                                                                                 93
     10(1H+))
  602 FORMAT (15(1H*), 44H ES SHOULD BE GREATER THAN OR EQUAL TO 0.0. ,51F14
                                                                                 94
                                                                            F14
                                                                                 95
     1(1H*))
  603 FORMAT (15(1H*), 44H ES SHOULD BE GREATER THAN OR EQUAL TO EGI. ,51F14
                                                                                 96
                                                                            F1A
                                                                                 97
     1(1H+))
  604 FORMAT (15(1H+),45H FOR A CONTINUOUS SPECTRUM, NC MUST EQUAL 1. ,5F14
                                                                                 98
                                                                                 99
                                                                            F14
     10(1H*))
  605 FORMAT (15(1H*), 49H ONLY 1 CONTINUOUS SPECTRUM PER SECTION ALLOWEDF14 100
```

SUBROUTINE FIL14(N)

	1. ,46(1H+)) F14 101	
62	606 FURMAT (15(1H*), 48H ES SHOULD BE EQUAL TO THE ABSOLUTE VALUE OF Q.F14 102	
	1 ,47(1H*)) F14 103	
63	607 FORMAT (15(1H*),25H ALL ES SHOULD BE EQUAL, ,73(1H*)) F14 104	
64	608 FERMAT (15(1H*), 33H EGI MUST BE IN DECENDING DRDER. ,62(1H*)) F14 105	
65	609 FORMAT (15(1H*), 29H NP MUST BE GREATER THAN NR. ,65(1H*)) F14 106	
66	610 FURMAT (15(1H*), 72H INTERPOLATION SCHEME IS REQUIRED TO BE LINEAR F14 107	
	1THROUGHOUT ENTIRE RANGE. ,23(1H+)) F14 108	
67	611 FURMAT (15(1H*),64H INTERPULATION SCHEME SHOULD BE LINEAR THROUGHOF14 109	
	101 ENTIRE RANGE. ,31(1H*)) F14 110	
68	612 FURMAT (15(1H*), 68H INCIDENT NEUTRON ENERGY LESS THAN EFFECTIVE THE 111	
	1RESHOLD IN FILE 3(= ,1PE12.5,3H). ,12(1H*)) F14 112	
69	613 FURMAT (15(1H+),55H INCIDENT NEUTRON ENERGIES MUST BE IN ASCENDINGF14 113	
	1 BROER. ,40(1H*)) F14 114	
70	614 FORMAT (15(1H+),47H DISTRIBUTION SHOULD BE ENTERED ISOTROPICALLY. F14 115	
	1,48(1H*)) F14 116	
71	615 FURMAT (15(1H+),54H FUR NC EQUAL 1, THERE MUST BE A CONTINUOUS SPEF14 117	
	1CTRUM.,41(1H*)) F14 118	
72	616 FORMAT (15(1H*)>3/H FOR EGI EQUAL TO 0.0, NC MUST BE 1. ,58(1H*))F14 119	
73	617 FURMAT (15(1H+),54H THERE CAN BE NO CUNTINUOUS SPECTRUM IN THIS SEF14 120	
	1CTION. ,41(1H*)) F14 121	
74	END F14 122-	,

INDEX PAGE 19

SYMBOL		= = =	= = = =	= = =	= = =	REFERE	NCES		= = = =		* * *
1	-	6	7 *								
2	-	9	20*								
3	-	20	23*								
3 4 5 6 7	-	26	30*								
5	- ,	14	15	19	29	33*					
6	-	6	36*			• • • • • • • • • • • • • • • • • • • •					
7	-	40	41*								
8	-	41	43*								
9	-	6	44*								
10	-	6	53*								
601	-	IOWR	21WR	57*							
602	-	11WR	22WR	58*							
603	-	12WR	23WR	59*							
604	-	17WR	60*								
605	-	18WR	61*								
606	-	24WR	62*								
607	-	30WR	63*								
608	-	31WR	64*								
609	-	33WR	65*								
610	-	34WR	66*								
611	-	36WR	67*								
612	_	37WR	53WR	68*							
613	-	38 W R	54WR	69*							
614	-	42WR	70*								
615	_	44WR	71*								
616	-	45WR	72*								
617	-	46WR	73*								
ABS		24	, , , ,								
В	-	300									
C 1	-	300	11	12	15	22	23	24	27	30	
Ç2	-	300	10	12	15	20	23	28	31	32	37
~ _		38	39	53	54	55			••		٠.
COUN	-	200	•		- ,	-					
EG	-	5C0	13=	28=	31	32=	45	47=			
ĒK	-	400	10-		•	J-	. 2	••			
EN	-	500	38	39=	48=	54	55≖				
ES	-	400	•								
ESEGPR	-	8									
ESI	-	500	27=	30	49=						
ETAB		400									
ETH	-	400	37	53							
FIL14	•	1									
I	-	40	41								
IL	-	5¢0	16=	17	18	44	45	50=			
IN	-	500	25≈	26	51=						
JNT	-	3 C O	34	36	-						
L1	-	300	- ·								
L2.	-	300									
₩ E.											

INDE	Х.								PAGE	20
					SUBROUT	INE FILT	4(N)			
LG	-	200								
MAT	-	3 C (1)								
MF	-	300								
MT	-	300	Q	14	24	37	46	53		
N	-	1 A G	6							
N 1	-	300	33	34	36					
N1X	-	3 C O								
N2	-	300	7	33	40	42				
N2X	-	300								
NBT	-	3 C O								
NC	-	200	17	44	46					
ND	-	50 0								
NE	-	2 00	7 =							
NI	-	5C 0								
NK	-	2C D								
NP	-	2¢0								
NS	-	300								
NS1	-	2¢0								
NTAB	-	200								
Q	-	400	24							
RECS	-	300	_		_					
RETURN	-	35	43	52	56					
SAV14	•	500								
SAVE	-	4C0								
X	•	300								
Y	-	300	41							
YCAL	-	400								
YK	-	4 C O								
YKTAB	-	4CO								
YTAB	-	400								
YTIL	-	400								

PAGE 21 INDEX SUBROUTINE FIL15(N) SUBROUTINE FIL15(N) F15 1 F15 COMMON/COUN/LG, NC, ND, NE, NI, NK, NP, NTAB, NS1 2 2 COMMON/RECS/MAT, MF, MT, C1, C2, L1, L2, N1, N2, NBT(100), JNT(100), X(2000), F15 3 3 Y(2000),B£2000),N1X,N2X,NS F15 4 1 CBMMDN/SAVE/ETH(300), @(300), ETAB(2000), YTAB(2000), YKTAB(2000), F15 5 4 YCAL(2000), YTIL(2000), EK(2000), YK(2000), ES(40) F15 6 1 COMMON/SAV15/A(2000) F15 7 5 GO TO (1,3,10,11,13,19,26,29), N F15 8 6 F15 9 C----STORE TABULATED ENERGIES AND YIELDS. F15 10 C F15 11 F15 7 1 D8 2 J = 1, N2 12 ETAB(I) = X(I)F15 13 8 F15 2 YIAR(I) = Y(I)14 Q F15 15 NTAR = N21.0 IF (FTAB(1) .LT. ETH(MT)) WRITE (6,601) ETH(MT) F15 16 11 F15 17 12 RETURN F15 18 C F15 C=====LF = 1 19 STORE SECTION ENERGIES AND YIELD. F15 20 C F15 21 C F15 22 3 DQ 4 I = 1, N213 F15 23 EK(I) = X(I)14 F15 24 15 4 YK(I) = Y(I)F15 25 16 NP = N2F15 26 C C TEST ENERGIES. F15 27 F15 28 С IF (EK(1) +LT. ETH(MT)) WRITE (6,601) ETH(MT) F15 29 17 IF (EK(1).LT.ETAB(1) .OR. EK(NP).GT.ETAB(NTAB)) WRITE (6,602) F15 30 18 F15 19 CALL ESEGPR(2) 31 F15 32 C C CALCULATE SECTION YIELDS FOR TABULATED ENERGIES. F15 33 F15 3Δ F15 35 20 D0 9 I = 1, NTAB F15 21 L = N2 - 136 F15 37 22 K = 0F15 38 80 5 J = 1, L 23 F15 39 24 K = K + 1IF (EK(J) .EQ. ETAB(I)) GO TO 6 F15 40 25 F15 41 5 IF (EK(J).LT.ETAB(I) .AND. EK(J+1).GT.ETAB(I)) GO TO 7 26 F15 42 K = K + 127 F15 43 28 IF (EK(N2) .EQ. ETAB(I)) GO TO 6 F15 44 29 GO TO 9 6 YNTAB(I) = YK(K) F15 45 30 F15 46 GB TO 9 31 F15 47 7 D0 8 J = 1, N132 8 IF (K .LE. NBT(J)) INT = JNT(J) F15 48 33 CALL TERP1(EK(K), YK(K), EK(K+1), YK(K+1), ETAB(I), YKTAB(I), INT) F15 49 34 F15 50

9 YEAL(I) = YCAL(I) + YRTAB(I)

TNDEX	CHARGUTINE ETLISON)	PAGE	22
	SUŖROUTINE FIL15(N)		
36	RETURN	F15	51
30	C	F15	52
	CTEST TAB2 RECURD.	F15	53
	c	F15	54
37	10 NE = N2	F15	55
. 38	IF (NE .NE. NP) WRITE (6,603)	F15	56
39	IF (N1.NE.1 .UR. JNT(1).NE.2) WRITE (6,604)	F15 F15	57 58
40	RETURN	F15	59
	C CALCULATE TOTAL YIELD.	F15	60
	· ·	F15	61
4.4	11 NI = NI + 1	F15	62
41	C	F15	63
	C TEST ENERGIES.	F15	64
	C	F15	65
42	IF (C2 .LT. ETH(MT)) WRITE (6,605) ETH(MT)	F15	66
43	IF (C2 .LT. EK(NI)) WRITE (6,606)	F15	67
44	L = N2 - 1	F15	68
	C	F15	69
	C INTEGRATE PHOTON YIELD PROBABILITIES.	F15	70
	C	F15	71
45	DU 12 I = 1, L	F 1 5	72
46	A1 = A1 + (X(1+1) + X(1)) + (Y(1+1) + Y(1))/2 + 0	F15 F15	73 74
47	$12 \ A2 = A2 + (X(I+1)=X(I))*(X(I+1)*Y(I+1)+X(I)*Y(I))/2.0$ IF (ABS(A1=1.0000) .GT. 0.0001) WRITE (6,607) A1	F15	75
48	A(NI) = A2/A1	F15	76
49 50	A2 = 0.0	F15	77
51	A1 = 0.0	F15	78
52	RETURN	F15	79
53	13 DH 18 I = 1, NTAB	F15	80
54	L = N2 - 1	F15	81
55	K = 0	F15	82
56	00 14 J = 1, L	F15	83
57	K = K + 1	F15 F15	84 85
58	IF (EK(J) .EQ. ETAB(I)) GO TO 15 14 IF (EK(J).LT.ETAB(I) .AND. EK(J+1).GT.ETAB(I)) GO TO 16	F15	86
59 60	K = K + 1	F15	87
61	IF (EK(NZ) .EQ. ETAB(I)) GO TO 15	F15	88
62	GO TO 17	F15	89
63	15 A3 = A(K)	F15	90
64	GB TO 17	F15	91
65	16 CALL TERPICEK(K), A(K), EK(K+1), A(K+1), ETAB(I), A3,2)	F15	92
66	17 YTIL()) = YTIL(1) + YKTAB(1)*A3	F15	
67	18 A3 = 0.0	F15	94
68	RETURN	F15	95 94
		F15 F15	96 97
	C	F15	98
	C TEST ENERGIES.	F15	99
69	19 IF (X(1) .LT. ETH(MT)) WRITE (6,601) ETH(MT)	F15	100

PAGE 23 INDEX SUBROUTINE FIL15(N) IF (X(1).LT.ETAB(1) .QR. X(N2).GT.ETAB(NTAB)) WRITE (6,602) F15 101 76 F15 102 CALL ESEGPR(2) 71 F15 103 C F15 104 CALCULATE SECTION YEILDS FOR TABULATED ENERGIES. C F15 105 C F15 106 DO 25 I = 1, NTAB 72 L = N2 = 1F15 107 73 F15 108 74 K = 0F15 109 75 DO 20 J = 1, L F15 110 76 K = K + 1IM (X(J) .EQ. ETAB(I)) GO TO 21 F15 111 77 20 IF (X(J).LT.ETAB(I) .AND. X(J+1).GT.ETAB(I)) GO TO 22 F15 112 78 F15 113 K = K + 179 IF (X(N2) .EQ. ETAB(I)) GO TO 21 F15 114 80 F15 115 GU TO 24 81 F15 .116 21 YRTAB(I) = Y(K)82 F15 117 83 GU TO 24 F15 118 84 22 DQ 23 J = 1 N123 IF (K .LE. NBT(J)) INT = JNT(J) F15 119 85 CALL TERPICX(K), Y(K), X(K+1), Y(K+1), ETAB(I), YKTAB(I), INT) F15 120 86 F15 121 C F15 122 CALCULATE TOTAL YIELD. С F15 123 F15 124 24 YCAL(I) = YCAL(I) + YRTAB(I)87 25 YTIL(I) = YTIL(I) + YMTAB(I)*C2 F15 125 38 F15 126 RETURN 89 C F15 127 F15 128 C----TEST TOTAL YIELD. F15 129 26 DU 27 I = 1, NTAB YDIFF = (YTAB(I) - YCAL(I))/YCAL(I) F15 130 90 F15 131 91 IF (ABS(YDIFF) .. GT. 0.0001) WRITE (6,600) YTAB(I), YCAL(I), ETAB(I) F15 132 92 IF (((MT.GE.5 .AND. MT.LE.14) .OR. (MT.GE.51 .AND. MT.LE.80)) .ANDF15 133 93 1. YTIL(I).GT.ABS(Q(MT))) WRITE (6,609) YTIL(I),Q(MT),ETAB(I) F15 134 27 IF ((MT.LE.4 .OR.(MT.GE.15 .AND. MT.LE.50) .OR. MT.GE.81) .AND. YTF15 135 94 F15 136 11L(T).GT.(Q(MT)+LTAB(1))) WRITE (6,610) YTIL(I), ETAB(1) F15 137 C F15 138 C----RE-INITIALIZE. F15 139 C F15 140 D0 28 I = 1, 200095 F15 141 A(I) = 0.096 F15 142 EFAB(I) = 0.097 F15 143 98 $\mathsf{EK}(\mathsf{I}) = \mathsf{O} \cdot \mathsf{O}$ F15 144 YTAR(I) = 0.099 F15 145 100 YCAL(I) = 0.0YRTAR(I) = 0.0F15 146 101 102 YK(I) = 0.0F15 147 103 28 YTIL(I) = 0.0F15 148 F15 149 NI = 0104 F15 150 RETURN 105

INDE	«	PAGE 24
	SUBROUTINE FIL15(N)	
	•	F15 151
	C CTEST LG.	F15 151
	C C	F15 153
106	29 GH TO (30,34,39), LG	F15 154
100	C	F15 155
	COHT[N 1	F15 156
	C CHECK 2NT = 2 * NT	F15 157
	C	F15 158
107	30 IF (N1 .E0. (2*N2)) GO TO 31	F15 159
108	WRITE (6,611)	F15 160
109	N1 = 2 * N2	F15 161
	C	F15 162
	C TEST ENERGIES.	F15 163
	(F15 164
110	31 IF (B(1) .GE. C1) WRITE (6,612) IF (C1 .LT. ABS(Q(MT))) WRITE (6,613)	F15 165 F15 166
111	00.32 I = 3, N1, 2	F15 167
112 113	32 IF (R(I).GE.B(I=2) .AND. N1.NE.2) WRITE (6,614) B(1)	F15 168
114	CALL STATE(LG)	F15 169
115	CALL ESEGPR(3)	F15 170
•••	C	F15 171
	C TEST TP ARRAYS.	F15 172
	C	F15 173
116	$D0.33 I = 2 N1 \cdot 2$	F15 174
117	IF (R(I) .LE. 0.0) WRITE (6,615) B(I-1)	F15 175
118	IF (B(I) .GT. 1.0) WRITE (6,616) B(I-1)	F15 176
119	33 TP = TP + B(I)	F15 177
120	IA (TP .LE. 0.9999) WRITE (6,617) TP	F15 178
121	IP (TP .GT. 1,0001) WRITE (6,618) TP	F15 179
122	TP = 0.0	F15 180
123	RETURN	F15 181 F15 182
	C COMMON CONTROL O	F15 183
	COPTION 2 = 3 * NT	F15 184
	C CHECK 3NT = 3 * NT	F15 185
124	34 IF (N1 .EQ. (3×N2)) GO TO 35	F15 186
125	HRITE (6,611)	F15 187
126	N1 = 3 * N2	F15 188
•	C	F15 189
	C TEST ENERGIES.	F15 190
	C	F15 191
127	35 IF (8(1) .GL. C1) WRITE (6,612)	F15 192
128	IF (C1 .LT. ABS(Q(MT))) WRITE (6,613)	F15 193
129	Ou 36 I = 4, N1, 3 36 IF (B(I),GE.B(I=3) .AND. N1.NE.3) WRITE (6,614) B(I)	F15 194 F15 195
130 131	CALL STATE(LG)	F15 196
131	CALL ESEGPR(4)	F15 197
132	C	F15 198
	C TEST TP ARRAYS.	F15 199
	C	F15 200

IN	D E	_ x	PAGE	25
• .,		SUBROUTINE FIL15(N)		
1	33	$00 \ 37 \ I = 2 \ N1 \ 3$	F15	201
	34		F15	
-	35		F15	
	36		F15	204
	37		F15	
	38		F15	
	39		F15	207
		\mathbf{c}	F15	208
			F15	209
		c	F15	210
1	40	DU 38 τ = 3, N1, 3	F15	211
1	4.1		F15	212
1	42		F15	
1	43		F15	
			F15	
		V CONTRACTOR OF THE CONTRACTOR	F15	
			F15	
	44		F15	
	45	· · · · · - ·	F15	
	46		F15	
1	47	601 FORMAT (15(1H*),5/H FIRST ENERGY LESS THAN EFFECTIVE THRESHOLD IN		
	h 3	1 FILE 3(= >1PE12.5>3M). >23(1H+)) 6U2 FORMAT (15(1H+)>87H SUB-SECTION YIELD ENERGY RANGE EXCEEDS (BELOW	F15	
1	48		F15	
	49	603 FORMAT (15(1H*), 48H NE NOT EQUAL TO NP. NE ASSUMED TO BE CORRECT.		
1	47		F15	
1	50	604 FORMAT (15(1H*),64H INTERPOLATION SCHEME SHOULD BE LINEAR THROUGHO		
			F15	
1 '	51	605 FORMAT (15(1H*), 69H INCIDENT NEUTRON ENERGY LESS THAN EFFECTIVE TH	F15	229
-		1RESHOLD IN FILE 3(= >1PE12.5,3H). 11(1H*))	F15	230
1	52	606 FURMAT (15(1H*),72H INCIDENT NEUTRON ENERGY NOT EQUAL TO CORRESPON	F15	231
		1DING TOTAL YIELD ENERGY. ,18(1H*)/15(1H*),20H TOTAL YIELD ENERGY ,	F15	232
			F15	
1	53	607 FURMAT (15(1H*),49H THE INTEGRAL OF THE PHOTON YIELD PROBABILITY (
			F15	
1	54	608 FORMAT (15(1H*),69H TABULATED TOTAL YIELD NOT EQUAL TO TOTAL OF TH	F15	236
		1E SUR-SECTION YIELDS. ,26(1H*)/15(1H*),25H TABULATED TOTAL YIELD =	F 15	237
		2 ,1PE11.4,33X,26(1H*)/15(1H*),26H CALCULATED TOTAL YIELD = ,1PE11.		
		34,32X,26(1H*)/15(1H*),10H ENERGY = ,1PE11.4,48X,26(1H*)) 609 FURMAT (15(1H*),50H TOTAL MEV/INTERACTION EXCEEDS THAT ALLOWED BY	F15	
1	55	10. ,45(1H*)/15(1H*), 19H MEV/INTERACTION = ,1PE11.4,20X,45(1H*)/15	L 1 P	240
		2(1H+),5H R = 1PE11.4,34x,45(1H+)/15(1H+),10H ENERGY = 1PE11.4,29	F 15	242
				243
1	56	610 FURMAT (15(1H*), BOH TOTAL MEV/INTERACTION EXCEEDS THAT ALLOWED BY		
1		10 + E (INCIDENT NEUTRON ENERGY). , 15(1H*)/15(1H*), 19H MEV/INTERACT	F 15	245
		2IUN = ,1PE11.4,50X,15(1H*)/15(1H*),10H ENERGY = ,1PE11.4,59X,15(1H	F15	246
		(3*))	F15	247
1	57	611 FURMAT (15(1H*),52H FIFTH AND SIXTH FIELDS OF FIRST CARD DO NOT AG		
.,		1REE, ,43(1H*))	F15	249
1	58	612 FURMAT (15(1H*), 26H ES(1) NOT EQUAL TO ESNS. ,69(1H*))	F15	250

INDE		PAGE	26
	SUBROUTINE FIL15(N)		
159	613 FURMAT (15(1H*), 26H ES SHOULD BE EQUAL TO Q. ,69(1H*))		
160	614 FORMAT (15(1H+),27H ESI OUT OF ORDER AT ESI = ,1PE11,4,3H , ,54(1+))	F15	253
161	615 FORMAT (15(1H*),40H TPI LESS THAN OR EQUAL TO 0.0 AT ESI = ,1PE1 14,3H41(1H*))	1.F15 F15	_
162	616 FORMAT (15(1H*), 31H TPI GREATER THAN 1.0 AT ESI = ,1PE11.4,3H 10(1H*))		256
163	617 FURMAT (15(1H*), 2BH TUTAL TP LESS THAN 0.9999. ,67(1H*)/15(1H*), 1 1P = ,F12.5,10X,67(1H*))		258
164	618 FURMAT (15(1H*),31H TOTAL TP GREATER THAN 1.0001. ,64(1H*)/15(1H	+)F15	260
165	1,6H TP = ,1PE12,5,13X,64(1H*)) 619 FORMAT (15(1H*),40H GPI LESS THAN OR EQUAL TO 0.0 AT ESI = ,1PE1:		262
166	14,3H . ,41(1H*)) 620 FURMAT (15(1H*),31H GPI GREATER THAN 1.0 AT ESI = ,1PE11.4,3H		264
167	10(1H*)) END	F15 F15	265 266=

INDEX PAGE 27

SYMBOL		= = = =		= = = =	= = =	REFERENCES	5 2 2 2	 = = = =	= = =
1	-	6	7*						
	-	7	9*						
2 3 4	-	6	13*						
4	-	13	15*						
5		23	26*						
5 6	-	25	28	30*					
7	-	26	32*						
8	-	32	33*						
9	-	20	29	31	35*				
10	-	6	37*						
11	-	6	41*						
12	-	45	47★						
13	-	6	53*						
14	-	>6	59*						
15	-	58	61	63*					
16	-	59	65*						
17	-	62	64	66*					
18	-	53	67*						
19	-	6	69*						
20	-	15	78∗						
21	•	17	80	82*					
22	-	18	84*						
23	-	84	85*						
24	-	81	83	87*					
25	-	12	88*						
26	-	6	90*						
27	-	90	94*						
28	. =	9 5	103*						
29	-	6	106*						
30	-	106	107*	146					
31	-	107	110*						
32	•	112	113*						
33	•	116	119*						
34	_	106	124*	145					
35		124	127*						
36	_	129 133	130*						
37 38	-	140	136* 142*						
39		146	144*						
601	_	11WR	144×	69 W R	147*				
602	•	18WR	70WR	148*	141*				
603	•	38WR	149*	1404					
604	-	39WR	149* 150*						
605	-	42 K K	150× 151×						
606	•	43WP	152*						
607	-	48WR	153*						
608	_	Y2WR	154*						
609		93WR	155*						
007	-	, 3 m M	100#						

PAGE 28 INDEX

					20 64001	INC LIE	CNIC				
610	-	94 N R	156*								
-	_	108WR	125WR	157*							
611	_	110WR		158*							
612	-		127WR								
613		111WR	128WR	159*							
614	-	113WR	130WR	160*							
615	-	117WR	134WR	161*							
616	-	118WR	135WR	162*							
617	-	120WR	137WR	163*							
618	-	121WR	138WR	164*							
619	-	141WR	165*								
650	-	142WR	166*								
Α	-	500	49=	63	65AG	9.6=					
A 1	-	46=	48	49	51=						
A 2	-	47=	49	50=							
A 3	-	63=	65AG	66	67=						
ABS	-	48	92	93	111	128					
8	-	3CO	110	113	117	118	119	127	130	134	135
		136	141	142							
C 1	-	300	110	111	127	128					
C 2	•	300	42	43	98						
COUN	-	2C0									
EΚ	-	4 C O	14=	17	18	25	26	28	34AG	43	58
		59	61	65AG	98=						
ES	-	4 C D									
ESEGPR	•	19	71	115	132						
ETAB	•	400	8=	11	18	25	26	28	34 A G	58	59
		61	65AG	70	77	78	80	86AG	92WR	93WR	94
		97=									
ETH	-	4 C O	11	17	42	69					
FIL15	-	1									
FLOAT	•	144									
I	-	7	8	9	13	14	15	20	25	26	28
•		30	34AG	35	45	46	47	53	58	59	61
		65AG	66	72	77	78	80	82	86AG	87	88
		90	91	92WR	93	94	95	96	97	98	99
		100	101	102	103	112	113	116	117	118	119
		129	130	133	134	135	136	140	141	142	11,
INT	-	33=	34AG	85=	BEAG			• • •		• "-	
j	-	23	25	26	32	33	56	58	59	75	77
•		18	84	85		•			-	• •	
JNT	-	300	33	39	a 5						
K	-	22=	24=	27=	30	33	34AG	55≖	57=	60=	63
		65AG	74=	76=	79=	82	85	86AG			
L	-	21=	23	44=	45	54=	56	73=	75		
Ī1	-	300		-	-	<u> </u>					
L2	••	300									
LG.	-	200	106	114AG	131AG						
MAT	-	300									
MF	-	300									
MT	•	3CO	11	17	42	69	93	94	111	128	
										-	

INDE	X										PAGE 29
					SUBROUT	INE FIL1	5(N)				
N	-	1 A G	6								
Ñ1	-	300	32	39	84	107	109=	112	113	116	124
•		126=	129	130	133	140	144			•••	154
N1X	•	300					• ,				
N2	•	300	7	10	13	16	21	28	37	44	54
- 2		b 1	70	73	80	109	126	144	•	• •	
N2X	-	300			•		-				
NBT	-	300	33	85							
NC	•	200	-								
ND	•	200									
NE	•	200	37 =	38							
NI	-	200	41=	43	49	104=					
NK	-	200									
NP	•	500	16=	18	38						
NS	-	300		_	_						
NS1	•	200									
NTAB	**	200	10=	18	50	53	70	72	90		
Q	•	4 C ()	93	94	111	128					
RATIO	•	144=	145								
RECS	•	3 C U									
RETURN	•	12	36	40	52	68	89	105	123	143	
SAV15	•	500									
SAVE	•	4 C 🖰									
STATE	-	114	131								
TERP1	~	34	65	86							
TP	-	119=	120	121	122=	136=	137	138	139=		
X	•	3Ca	8	14	46	47	69	70	77	78	80
		66AG									
Y	**	3C0	9	15	46	47	82	86AG			
YCAL	•	400	35=	87=	91	92WR	100=				
YDIFF	-	91≈ 	92		****						
YK	-	400	15=	30	34AG	102=					
YKTAB	•	400	30=	34AG	35	66	82=	86AG	87	88	101=
YTAB	~	400	9=	91	92WR	99=					
YIIL	-	400	66=	88=	93	94	103=				

ESG

ESG

ESG

ESG

47

48

49

50

00 11 1 = 1, M

I1 = NTB + 1

11 NTB = NTB + NESEGP(I)

12 = NTB + NESEGP(MT)

33

34

35

IND	E X	PAGE	31
	SUBROUTINE ESEGPR(N)		
37	DB 12 I = 1, N1, 3	ESG	51
38	D0 12 J = I1, I2	ESG	52
39	EG = C1 - B(I)	ESG	53
40	12 IF $(ESP(J) \cdot EQ \cdot C1 \cdot AND \cdot EGP(J) \cdot EQ \cdot EG) \cdot NPU(I) = 1$	ESG	54
41	13 RETURN	ESG	55
	c	ESG	56
	CCMECK ALL ES-EG PAIRS USED.	ESG	57
	C	ESG	58
42	14 UB 17 I = 1, NPS	ESG	59
43	IF (NPU(I) .EQ. 1) GO TO 17	ESG	60
44	DB 15 v = 10 300	ESG	61
45	K = J	ESG	62
46	NTB = NTB + NESEGP(I)	ESG	63
47	15 IF (NTB .GE. I) GO TO 16	ESG	64
48	16 WRITE (6,601) K,ESP(I),EGP(I)	ESG	65
49	NTB = 0	ESG	66
50	17 CONTINUE	ESG	67
51	RETURN	ESG	68
52	6∪1 FORMAT (15(1H*),41H THE FOLLOWING ES=EG PAIR, GIVEN IN MT =		69
	= 14 / 15(1/4+)/15(1H+), WAS NUT REFERENCED IN FILE 15. م 17(1H+)	,1PE12ESG	70
	$1.5,21X,6H$ EG = $\sqrt{1PE12.5},21X\sqrt{1H+1}$	ESG	71
53	END	ESG	72-

INDEX PAGE 32

SYMBOL		= = = =	= = = =	= = =	= = =	REFERE	NCES =		- = = = :		= =
1	-	5	6∗								
2	-	5	11*								
3	-	13	14*								
4	-	17	18*								
5	•	11	19*								
6	-	5	20*								
7		22	23*								
8	-	26	27	29*							
9	-	20	30*								
10	-	5	31×								
11	-	33	34*								
12	-	37	38	40*							
13	-	31	41*	70.							
14		5	42*								
15	-	44	47*								
16	-	47	48*								
17	-	42	43	.50×							
601		48WR	52 *	. 30							
В		300	28	39							
Č 1	-	300	8	18	28	29	39	40			
C 5	_	300	9	18	20	27	3,4	. 40			
COUN		2C0	,	10							
EG	_	28=	29	39=	40						
	_	4CU	9=			4.0	# O W C				
EGP	_	400	9=	18	29	40	48 W R				
ESEG	_										
ESEGPR	_	1		4.0							
ESP	-	400	8=	18	29	40	48 WR				
I	7	13	14	17	18	22	23	26	28	29	33
		34	37	39	40	42	43	46	47	48WR	
I 1	-	15=	17	24=	27	35=	38				
15	•	16=	17	25=	27	36=	38				
J	-	27	29	38	40	44	45				
JNT	-	3 C D									
K	-	45=	48WR								
i. 1	•	3¢0									
1.2	•	3 c 0									
LG	-	200		_	_						
М	-	12=	13	21=	22	32=	33				
MAT	•	3 C O									
MF	-	3CO									
MT	-	3C0	6	11	12	16	20	21	25	31	32
		36									
N	-	1 A G	5								
N 1	-	3C0	26	37							
N1X	•	3¢0									
N2	-	300									
N5X	-	300									
NBT	-	3CO									

200 200 200 400 36	6 =		SUBROUTI	NE ESEGF	r(n)				
200 200 400	6=								
200 400	6=								
4 C O	6=								
	6=								
4.6		11	14	16	20	23	25	31	34
	46								•
5 C0									
200									
200									
4 C O	· 7 =	8	9	42					
4 C D	18=	29=	40=	43					
3 C D									
200									
200									
14=	15	16	23=	24	25	34=	35	36	46=
47				_				_	, •
300									
10	19	30	41	51					
300			-	-					
300									
•	200 200 400 400 300 200 200 14= 47 300 10 300	200 200 400 7= 400 18= 300 200 200 14= 15 47 49= 300 10 19 300 300	200 200 400 7= 8 400 18= 29= 300 200 200 14= 15 16 47 49= 300 10 19 30 300 300	200 200 400 7= 8 9 400 18= 29= 40= 300 200 200 14= 15 16 23= 47 49= 300 10 19 30 41 300 300	200 200 400 7= 8 9 42 400 18= 29= 40= 43 300 200 200 14= 15 16 23= 24 47 49= 300 10 19 30 41 51 300 300	200 200 400 7= 8 9 42 400 18= 29= 40= 43 300 200 200 14= 15 16 23= 24 25 47 49= 300 10 19 30 41 51 300 300	200 200 400	200 200 400 7= 8 9 42 400 18= 29= 40= 43 300 200 200 200 14= 15 16 23= 24 25 34= 35 47 49= 300 10 19 30 41 51 300 300	200 200 400 7= 8 9 42 400 18= 29= 40= 43 300 200 200 200 14= 15 16 23= 24 25 34= 35 36 47 49= 300 10 19 30 41 51 300 300

INDE	. X	PAGE	34
	SUBROUTINE STATE(LG)		
1	SUBROUTINE STATE(LG)	STA	1
ž	CBMMON/RECS/MAT, MF, MT, C1, C2, L1, L2, N1, N2, NBT(100), JNT(100), X(2000),		ż
-	1 Y(2000),B(2000),N1X,N2X,NS	STA	3
3	COMMON/SAVE/ETH(300), 6(300), ETAB(2000), YTAB(2000), YKTAB(2000),	STA	4
_	1 YCAL(2000),YT1L(2000),EK(2000),YK(2000),ES(40)	STA	5
	C	STA	6
	C-=STORE ES.	STA	7
	c	STA	8
4	IF (MT.LE.4 .UR. (MT.GE.15 .AND. MT.LE.50) .OR. MT.GE.81) GO TO 3		9
5	IF (MT.GE.5 .AND. MT.LE.14) NOST = MT - 4	STA	10
6	IF (MT.GE.51 .AND. MT.LE.80) NOST = MT = 40	STA	11
7	ES(NOST) = C1	STA	12
	c	STA	13
	CTEST ES.	STA	14
	C FOR LG = $1 \cdot N = 2 \cdot$	STA	15
	$C \qquad \qquad FOR I.G = 2 N = 3 .$	STA	16
	c	STA	17
8	N = LG + 1	STA	18
9	$DG 2 I = 1 \cdot N1 \cdot N$	STA	19
10	DS 1 J = 1, $NOST$	STA	20
11	1 IF (B(I) .EQ. ES(J)) GO TO 2	STA	21
12	IF (B(I) •E9• 0•0) GD TO 2	STA	22
13	WRITE (6,601) B(I)	STA	23
14	2 CONTINUE	STA	24
15	3 RETURN	STA	25
16	601 FORMAT (15(1H+),56H EST MUST BE EQUAL TO ONE OF THE PREVIOUS STATE	STA	26
	1 LEVELS. , 39(1H*)/15(1H*), 23H THE EST IN QUESTION = ,1PE11.4,22x,3	STA	27
	19(1+*))	STA	28
17	END	STA	29-

INDEX

SYMBOL		= = = =	= = = =	= = =	2 = 2	REFERENCES	
1	-	10	11*				
2	•	9	11	12	14*		
3	-	4	15*				
601	•	13WR	16*				
8 C 1	•	200	11	12	13WR		
C 1	-	2C 0	7				
CS	-	2 C O		1			
EK	-	3 C O			,		
ES	-	3C0	7 =	11			
ETAB	-	3 C O					
ETH	-	3 C O					
I	-	9	11	12	13WR		
J JNT	-	10	11				
JNT	-	200					
L1	-	200					
L 1 L 2	•	200					
LG	-	1 A G	8				
MAT	-	-200					
MF	-	200					
MT	-	200	4	5	6		
Ň	•	8=	9				
N1	-	200	9				
N1X	-	200					
N2		200					
N2X	-	2C0					
NBT	-	200					
NOST	-	5=	6=	7	10		
NS	-	200					
Q	-	300					
RECS	-	200					
RETURN	•	15					
SAVE	-	3 C O					
STATE	•	1					
X Y	-	200					
	-	200					
YCAL	-	300					
YK	-	3 C O					
YKTAB	-	300					
YTAB	-	300					
YTIL	-	3CQ					

I N D	E X SUBROUTINE TEST2C(MT)	PAGE	36
	308/001146 /23/2004/7		
1	SUBROUTINE TEST2C(MT)	T2C	1
	C=====TEST REACTION TYPE, MT, FUR FILE 14====================================	T2C	2
	C MT MUST RE IN THE RANGE 3-29, 51-80, 101-108, 110, 301-450	T2C	3
2	COMMON/TST2C/NIN≥NUUT>NPUN≥NT≥MAT>MF→MM≥NSEQ≥LRD>LFI≥LDD>LFP>ZA>AW	T2c	4
_	1R,MATP,MFP,MTP,NSEQP,NOPT,NSEQP1	T2C	5
3	NOUT = 6	T2C	6
4	NUPT = 0	T2C	7
5		T2C	8
6		TZC	ğ
7		T2C	10
8		T2C	11
9		T2C	12
10		TZC	13
11		TZC	14
12		T2C	15
13		TZC	16
14	150 IF(NOPT.E0.0)GU TO 152	T2C	17
15	WRITE(NOUT, 151)MI, NSEQP	T2C	18
16	151 FORMAT(37X,3HMT=14,29M INCORRECT SEQUENCE NUMBER,2X,16)	T2C	19
17	69 79 170	T2C	20
18	152 WRITE(NOUT, 153)MI	T2C	21
19		TZC	22
20		T2C	23
21		T2C	24-

,	. N I) F	Y	PA	GE	37
1	L N I	<i>)</i> [.	Α	T 🖛	1 G L	J 1

SUBROUTINE TEST2C(MT) REFERENCES SYMBOL 10 5* 20 5 6* 30 6 7× 7 8* 40 50 8 .9* 9 60 10* 10 11+ 70 11 12* 80 90 12 13* 9 14* 11 12 13 150 5 7 15WR 16* 151 14 152 18* 153 18WR 19* 20* 10 13 17 8 11 170 6 200 AWR LDD 200 LFI 2C0 200 LFP LRD 200 200 MAT MATP 200 MF 200 MFP 200 200 MM 8 9 10 11 12 7 13 MT 1 A G 5 6 15WR 18WR 200 MTP 200 NIN 14 15wR 200 NOPT 4 **=** 18WR 200 3= NOUT NPUN 200 NSEQ 200 200 15WR NSEQP NSEQP1 200 200 NT RETURN 20

PAGE 38 INDEX

> INDEX END OF COMPUTATION.

TEST2C

TST2C

ZA

1

200

ACKNOWLEDGEMENT

The assistance with this project of Messrs. Jason M. Cook, James A. Wright, and James F. Church is gratefully acknowledged. As students in the Department of Nuclear Engineering at the University of Virginia, they participated with enthusiasm and patience in many of the battles with tapes, codes, and computer systems. Mr. Wright contributed most of section 3, and Mr. Cook was primarily responsible for the programming of the PHOX code. Mr. Church performed most of the corrections of the UK and ENDF/B Data Files. The staff of the Radiation Shielding Information Center, especially Dr. R. W. Roussin, were very helpful in a cooperative effort to process the preliminary version of the translated data thru the CHECKER and PLOTFB codes. The characteristic willingness of the RSIC staff to assist in projects useful to the Shielding Community was again exemplified. Special thanks are due to Mr. M. K. Drake of BNL for his patient help in resolving questions concerning important but vexating minutiae of the data.

REFERENCES

- 1. Henry C. Honeck, "ENDF/B Specifications for an Evaluated Nuclear Data File for Reactor Applications," BNL 50066 (or ENDF 102), Brookhaven National Laboratory (1966; revised 1967).
- 2. Donald J. Dudziak (ed.), "ENDF/B Format Requirements for Shielding Applications," LA-3801 (or ENDF III), Los Alamos Scientific Laboratory (1967).
- 3. M. K. Drake, J. D. Garrison, and M. S. Alien, "Neutron and Gamma Ray Production Cross Sections for Sodium, Magnesium, Chlorine, Potassium, and Calcium," GA-7829 (or NDL-TR-89), Vols. I to VI, General Atomics (1967).
- 4. Quarterly Status Report on the Advanced Plutonium Fuels Program, July I to Sept. 30, 1968, LA-4073-MS, Los Alamos Scientific Laboratory (1969).
- 5. M. E. Battat, D. J. Dudziak, and R. J. LaBauve, "⁶Li and ⁷Li in ENDF/B Format," LA-3695-MS, Los Alamos Scientific Laboratory (1967).
- 6. Donald J. Dudziak and Jason M. Cook, "LUTE and LATEX, Special-Purpose Codes to Translate from Extended-UK to ENDF/B Format," Document Number NE-3383-102-69U (or ENDF-128). University of Virginia (1969).
- 7. Donald J. Dudziak, Alan B. Marshall and Robert E. Seamon, "LAPH, A Los Alamos Photon Production Multigroup Cross Section Code for ENDF/B," (to be published as an LA-report).
- 8. M. K. Drake, (Private Communication), Brookhaven National Laboratory (1969).
- 9. J. Felberbaum (ed.), "Description of the ENDF/B Processing Codes CHECKER, CRECT, DAMMET, and Retrieval Subroutines," BNL 13582 (or ENDF-110), Brookhaven National Laboratory (1967, revised 1969).

	• .		

Security Classification

Security Classification			
DOCUMENT CO	NTROL DATA - R&D		the overall report is classified)
1. ORIGINATING ACTIVITY (Corporate author)			RT SECURITY C LASSIFICATION
University of Virginia	Ī	IInc'	lassified
Charlottesville, Virginia 22901	•	26 GROUP	
		L	
3. REPORT TITLE	Unitaratedii et	TECTO	TO OF CROSS
TRANSLATION TO ENDF/B AND	"PH 19109" On	IECVIIA	IG OF CROSS
SECTIONS FOR SHIELDING			!
4. DESCRIPTIVE NOTES (Type of report and inclusive dates)	*****		
Final Report (1 February 1969 to 3	31 October 196	9)	
5. AUTHOR(S) (Last name, first name, initial)			
Donald J. Dudziak			,
6. REPORT DATE	74. TOTAL NO. OF PA	AGES	7b. NO. OF REFS
October 1969	109	!	9
sa. contract or grant no. DASA01-69-C-0029	94. ORIGINATOR'S REI	PORT NUM	BER(S)
	DASA-2379		•
b. PROJECT NO.	DAUL-EJ.,		ı
PC100	<u></u>		
c.		10(3) (Any	other numbers that may be assigned
d.	ENDF-130		1
10. AVAILABILITY/LIMITATION NOTICES			
This document has been approved to	for public rele	ase and	d sale; its
distribution is unlimited.	•		-
11. SUPPLEMENTARY NOTES	12. SPONSORING MILIT		1777
ı			pport Agency
ŀ	Washington,		
	(Attention:	Direct	tor)
13. ABSTRACT			

Evaluations of neutron interaction and photon production cross sections for sodium, magnesium, chlorine, potassium, and calcium have been translated from a modified-UK format into ENDF/B format. The data have been reviewed and revised to a minor extent, and can be used by the LAPH code to generate multigroup photon production cross section matrices. All data sets have been transmitted to the University of California, Los Alamos Scientific Laboratory, to the National Neutron Cross Section Center at BNL, and to the Radiation Shielding Information Center at ORNL. Several "physics" checks have been proposed for the photon data, and a FORTRAN IV code, PHOX, has been written to incorporate some of these checks.

Security Classification

	LIN	LINK A		(B	LINKC	
KEY WORDS	ROLE	WT	ROLE	WT	ROLE	WT
neutron interaction cross sections						
photon production cross sections					j	
sodium						
magnesium						
chlorine						
potassium						
calcium photon data checking code ENDF/B format						

INSTRUCTIONS

- 1. ORIGINATING ACTIVITY: Enter the name and address of the contractor, subcontractor, grantee, Department of Defense activity or other organization (corporate author) issuing the report.
- 2a. REPORT SECURITY CLASSIFICATION: Enter the overall security classification of the report. Indicate whether "Restricted Data" is included. Marking is to be in accordance with appropriate security regulations.
- 2b. GROUP: Automatic downgrading is specified in DoD Directive 5200.10 and Armed Forces Industrial Manual. Enter the group number. Also, when applicable, show that optional markings have been used for Group 3 and Group 4 as authorized
- 3. REPORT TITLE: Enter the complete report title in all capital letters. Titles in all cases should be unclassified. If a meaningful title cannot be selected without classification, show title classification in all capitals in parenthesis immediately following the title.
- 4. DESCRIPTIVE NOTES: If appropriate, enter the type of report, e.g., interim, progress, summary, annual, or final. Give the inclusive dates when a specific reporting period is covered.
- 5. AUTHOR(S): Enter the name(s) of author(s) as shown on or in the report. Enter last name, first name, middle initial. If military, show rank and branch of service. The name of the principal author is an absolute minimum requirement.
- 6. REPORT DATE: Enter the date of the report as day, month, year, or month, year. If more than one date appears on the report, use date of publication.
- 7a. TOTAL NUMBER OF PAGES: The total page count should follow normal pagination procedures, i.e., enter the number of pages containing information.
- 7b. NUMBER OF REFERENCES: Enter the total number of references cited in the report.
- 8a. CONTRACT OR GRANT NUMBER: If appropriate, enter the applicable number of the contract or grant under which the report was written.
- 8b, 8c, & 8d. PROJECT NUMBER: Enter the appropriate military department identification, such as project number, subproject number, system numbers, task number, etc.
- 9a. ORIGINATOR'S REPORT NUMBER(S): Enter the official report number by which the document will be identified and controlled by the originating activity. This number must be unique to this report.
- 9b. OTHER REPORT NUMBER(\$): If the report has been assigned any other report numbers (either by the originator or by the sponsor), also enter this number(s).
- 10. AVAILABILITY/LIMITATION NOTICES: Enter any limitations on further dissemination of the report, other than those

imposed by security classification, using standard statements such as:

- "Qualified requesters may obtain copies of this report from DDC."
- (2) "Foreign announcement and dissemination of this report by DDC is not authorized."
- (3) "U. S. Government agencies may obtain copies of this report directly from DDC. Other qualified DDC users shall request through
- (4) "U. S. military agencies may obtain copies of this report directly from DDC. Other qualified users shall request through
- (5) "All distribution of this report is controlled. Qualified DDC users shall request through

If the report has been furnished to the Office of Technical Services, Department of Commerce, for sale to the public, indicate this fact and enter the price, if known.

- 11. SUPPLEMENTARY NOTES: Use for additional explanatory notes.
- 12. SPONSORING MILITARY ACTIVITY: Enter the name of the departmental project office or laboratory sponsoring (paying for) the research and development. Include address.
- 13. ABSTRACT: Enter an abstract giving a brief and factual summary of the document indicative of the report, even though it may also appear elsewhere in the body of the technical report. If additional space is required, a continuation sheet shall be attached.

It is highly desirable that the abstract of classified reports be unclassified. Each paragraph of the abstract shall end with an indication of the military security classification of the information in the paragraph, represented as (TS), (S), (C), or (U).

There is no limitation on the length of the abstract. However, the suggested length is from 150 to 225 words.

14. KEY WORDS: Key words are technically meaningful terms or short phrases that characterize a report and may be used as index entries for cataloging the report. Key words must be selected so that no security classification is required. Identifiers, such as equipment model designation, trade name, military project code name, geographic location, may be used as key words but will be followed by an indication of technical context. The assignment of links, rules, and weights is optional.

,